



Tech Info Library

Apple IIc: Setting serial port 2's firmware from BASIC (2 of 2)

--Modem Port Command Codes:

1. Line width

- a. Code: A number from 1 through 255 followed by a carriage return.
- b. Code: A number from 1 through 255 followed by the letter N. This form of the command code also means that output will not be echoed to the screen.
- c. To turn off automatic generation of carriage return, either:
 1. use the Z command,
 2. use the System Utilities Disk.

2. Baud rate

Code	Rate
1B	50
2B	75
3B	110 (109.92)
4B	135 (134.58)
5B	150
6B	300
7B	600
8B	1200
9B	1800
10B	2400
11B	3600
12B	4800
13B	7200
14B	9600
15B	19200

3. Data format

Code	Data bits	Stop bits
0D	8	1
1D	7	1
2D	6	1
3D	5	1
4D	8	2
5D	7	2
6D	6	2

7D 5 2

4. Echo output on the screen

Code Effect

I Output is echoed on the screen.

5. Line feed after carriage return.

Code Effect

K A line feed is not sent after a carriage return.

L A line feed is sent after a carriage return.

6. Parity

Code Parity

0P None

1P Odd

2P None

3P Even

4P None

5P MARK (1)

6P None

7P SPACE (0)

7. Terminal Mode

Code Effect

T Enter Terminal Mode. Use this command after IN#2 only. If you follow this command by PR#2, the Apple IIc will echo input to output. If the other device does so too, the first character entered will loop endlessly, locking up the system. Use CTRL-RESET to get out.

Q Quit terminal mode.

8. Reset

Code Effect

R Reset port 2 and exit from serial port 2 firmware.

9. Break

Code Effect

S Send a 233 millisecond BREAK character.

10. Ignore

Code Effect

Z Zap (ignore) further command characters until CTRL-Reset.
NOTE: Do not format output or insert carriage returns into
output stream.

11. Terminal mode command codes from remote devices

Code Effect

CTRL-T If IN#2 is already in effect, this command puts the Apple IIC
in terminal mode, just as does the local command T.

CTRL-R This command undoes the remote terminal mode command. If IN#2
and PR#2 are in effect, the remote keyboard and display become
the input and output devices of the local Apple IIC.

WARNING: Apple IIC firmware DOES NOT allow you to use control characters B, C,
H, I, J, L, M, or Y: doing so may cause unpredictable effects.

Apple Technical Communications

Keywords: <None>

=====

This information is from the Apple Technical Information Library.

19960215 11:05:19.00

Tech Info Library Article Number: 1276