

7			8		
REV	ZONE	ECN	DESCRIPTION OF REVISION	CK APPD	ENG APPD
				DATE	DATE
PRO			PROTOTYPE RELEASE	5/29/98	5/29/98
EVT			EVTA RELEASE	6/20/98	6/20/98
EVT			EVTB RELEASE	7/20/98	7/20/98
DVT			DVT RELEASE	9/4/98	9/4/98
PRD			PVT RELEASE	10/9/98	10/9/98
A		67751	PRODUCTION RELEASE	11/98	11/98
B		68642	PRODUCTION UPDATE 1	12/98	12/98
C		69405	PRODUCTION UPDATE 1.1	1/99	1/99

.TABLE OF CONTENTS		
Section	Page	Description
Contents	1.	Cover Page
	2.	Technical Block Diagram
CPU	3.	CPU Interposer
	4.	CPU Core Voltage Regulator
Clocks	5.	System & PCI Clocks
	6.	SDRAM and Buffer Clocks
	7.	Zero Delay Clock Buffer
	8.	Other Clocks
Core Logic	9.	Memory Controller / PCI Host Bridge (Motorola Grackle)
DRAM	10.	SDRAM Control & PCI Arbitor (Apple GC-II)
	11.	SDRAM & ROM Address Buffers
	12.	SDRAM Data Latches
	13.	SDRAM DIMMs 0 & 1
	14.	SDRAM DIMMs 2 & 3
ROM	15.	Flash & Mask Boot ROM
Config	16.	Power, Fan & Scan Connectors
	17.	FPB/IrDA (Reset/NMI & IrDA) Connector
PCI	18.	66Mhz 32bit PCI Slot 1
	19.	PCI 66Mhz 32bit to 33Mhz 64bit Bridge (DEC 21154)
	20.	64bit 33Mhz PCI Slot 2
	21.	64bit 33Mhz PCI Slot 3
	22.	64bit 33Mhz PCI Slot 4
Legacy I/O	23.	I/O Controller ASIC (Apple Paddington)
	24.	ADB Controller and RTC (Apple Cuda)
	25.	Serial Modem Connector
	26.	ATA(3) / ATAPI Connector and NVRAM
Ethernet	27.	10/100 Ethernet Interface
	28.	Ethernet Transceiver and Connector
Ultra ATA	29.	Ultra ATA Controller (CMD 0646U2)
	30.	Ultra ATA Connector
USB	31.	USB Controller (CMD 0670)
	32.	USB Ports 1 and 2
	33.	USB Soft Power-On
FireWire	34.	FireWire Link Layer (TI Lynx)
	35.	FDB Interface and Bus Holders
Audio	36.	Audio Codec (Apple Burgundy)
	37.	DVD Analog and Digital Inputs
	38.	CD Analog Audio inputs
	39.	Microphone & Rear Headphone Jacks
	40.	Mono Amp & Speaker Connector
Other	41.	Caps, Plated holes & Reference Info
	42.	Reference Locators 1
	43.	Reference Locators 2
	44.	Revision History

PART NUMBER	QTY	DESCRIPTION	ASSOCIATED REFERENCE DESIGNATORS
820-1049-A	1	PCB, YOSEMITE MLB	PCB1


BOM OPTION
SPECIAL CHARACTERS
LEGEND
(PRECEEDS THE BOM OPTION NAME)


:"\$" = DEFAULT BOM OPTION
:"=" = COPY TO COOKED BOM
BUT DO NOT COOK


Cover Page


DIMENSIONS ARE EXPRESSED IN MILLIMETERS X.X★ X.XX★ X.XXX★ ANGLES★ DO NOT SCALE DRAWINGS		METRIC		Apple Computer, Inc	
		DRAFTER	DESIGN CK	NOTICE OF PROPRIETARY PROPERTY THE INFORMATION CONTAINED HEREIN IS THE PROPRIETARY PROPERTY OF APPLE COMPUTER, INC. THE POSSESSOR AGREES TO THE FOLLOWING (I) TO MAINTAIN THE DOCUMENT IN CONFIDENCE (II) NOT TO REPRODUCE OR COPY IT (III) NOT TO REVEAL OR PUBLISH IT IN WHOLE OR PART	
		ENG APPD	MFG APPD	TITLE	
		QA APPD	DESIGNER	SCHEM, MLB, PMG3	
		RELEASE	SCALE NONE	DRAWING NUMBER 051-0777	
		MATERIAL/FINISH NOTED AS APPLICABLE		SIZE D	REV. C
				SHT 1 OF 44	


ECS CAD GENERATED
APPLE CONFIDENTIAL












ECS CAD GENERATED
APPLE CONFIDENTIAL


NOTICE OF PROPRIETARY PROPERTY
THE INFORMATION CONTAINED HEREIN IS THE PROPRIETARY
PROPERTY OF APPLE COMPUTER, INC. THE POSSESSOR
HEREOF. IT IS NOT TO BE REPRODUCED OR COPIED IN ANY
MANNER WITHOUT THE WRITTEN PERMISSION OF APPLE
COMPUTER, INC. (i) TO MAINTAIN THE DOCUMENT IN CONFIDENCE
(ii) NOT TO REPRODUCE OR COPY IT
(iii) NOT TO REVEAL OR PUBLISH IT IN WHOLE OR PART


Zero Delay Buffer Clocks


Apple Computer, Inc.	SIZE	DRAWING NUMBER	REV
	E	051-0777	C
SCALE	NONE	SHT 7	OF 43





SIZE D	DRAWING NUMBER 051-0777	REV. C
SCALE NONE		SHT 8 OF 43














ECS CAD GENERATED
 APPLE CONFIDENTIAL






1 2 3 4 5 6 7 8


TRICKLE+5V (24,33,39)




FAN CONNECTOR SUPPORT				
PART NUMBER	QTY	DESCRIPTION	ASSOCIATED REFERENCE DESIGNATORS	BOM OPTION
515-1083	1	CON, 3P RT-ANGLE	J33	FAN POWER, STD
740S0505	1	FUSE, 2.5A 15V	F7	FAN POWER, STD
113S1274	1	RES, FF, 27K OHM, 5%, 1/16W	R207	FAN POWER, STD
515-1083	1	CON, 3P RT-ANGLE	J33	FAN POWER, PULSE
740S0505	1	FUSE, 2.5A 15V	F7	FAN POWER, PULSE
113S1274	1	RES, FF, 27K OHM, 5%, 1/16W	R207	FAN POWER, PULSE



SCAN CHAIN ORDER	
ICT	ESP
↓	↓
.CPU INTERPOSER	.CPU INTERPOSER
↓	↓
.MEM/PCI CNTLR	.SCAN CONNECTOR
↓	
.NORTH PCI ARBITOR	
↓	
.SOUTH PCI BRIDGE	
↓	
.J/O CONTROLLER	
↓	
.SCAN CONNECTOR	







NOTICE OF PROPRIETARY PROPERTY
THE INFORMATION CONTAINED HEREIN IS THE PROPRIETARY
PROPERTY OF APPLE COMPUTER, INC. THE POSSESSOR
AGREES TO THE FOLLOWING
(I) TO MAINTAIN THE DOCUMENT IN CONFIDENCE
(II) NOT TO REPRODUCE OR COPY IT
(III) NOT TO REVEAL OR PUBLISH IT IN WHOLE OR PART


ECS CAD GENERATED
APPLE CONFIDENTIAL


66Mhz 32bit PCI Slot 1

SIZE	D	DRAWING NUMBER	051-0777	REV.	C
SCALE	NONE	SHT	18	OF	43











NOTICE OF PROPRIETARY PROPERTY
 THE INFORMATION CONTAINED HEREIN IS THE PROPRIETARY
 PROPERTY OF APPLE COMPUTER, INC. THE POSSESSOR
 AGREES TO THE FOLLOWING:
 (I) TO MAINTAIN THE DOCUMENT IN CONFIDENCE
 (II) NOT TO REPRODUCE OR COPY IT
 (III) NOT TO REVEAL OR PUBLISH IT IN WHOLE OR PART

Apple Computer, Inc.

SIZE	DRAWING NUMBER	REV.
E	051-0777	C
SCALE	NONE	SHT 22 OF 43

ECS CAD GENERATED
 APPLE CONFIDENTIAL






ECS CAD GENERATED
APPLE CONFIDENTIAL

NOTICE OF PROPRIETARY PROPERTY
THE INFORMATION CONTAINED HEREIN IS THE PROPRIETARY
PROPERTY OF APPLE COMPUTER, INC. THE POSSESSOR
AGREES TO THE FOLLOWING
(I) TO MAINTAIN THE DOCUMENT IN CONFIDENCE
(II) NOT TO REPRODUCE OR COPY IT
(III) NOT TO REVEAL OR PUBLISH IT IN WHOLE OR PART

Apple Computer, Inc	SIZE D	DRAWING NUMBER 051-0777	REV. C
	SCALE NONE	SHT 27 OF 43	



PART NUMBER	QTY	DESCRIPTION	ASSOCIATED REFERENCE DESIGNATORS	BOM OPTION
519-0857	1	CONN, RJ45, SHIELD, 2 LEDS	J6	ENET LED, ENA
519-0389	1	CONN, RJ45 SHORT, SHIELD	J6	\$ENET LED, DIS

ECS CAD GENERATED
APPLE CONFIDENTIAL

NOTICE OF PROPRIETARY PROPERTY
THE INFORMATION CONTAINED HEREIN IS THE PROPRIETARY
PROPERTY OF APPLE COMPUTER, INC. THE POSSESSOR
AGREES TO THE FOLLOWING:
(I) TO MAINTAIN THE DOCUMENT IN CONFIDENCE
(II) NOT TO REPRODUCE OR COPY IT
(III) NOT TO REVEAL OR PUBLISH IT IN WHOLE OR PART

Ethernet Transceiver and Connector

SIZE D	DRAWING NUMBER 051-0777	REV. C
SCALE NONE	SHT 28 OF 43	

1		2		3		4		5		6		7		8																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																												
REFERENCE DESIGNATOR LOCATIONS																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																										
BT1 24-B2		C106 41-B7		C205 21-D4		C297 17-A6		C445 34-A1		C553 22-D4		C645 12-C2		C736 7-A6		C835 4-A7		L11 32-C7		R6 23-C7		R97 31-C2		R188 11-C4																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																		
C1 26-B4	C2 41-C6	C3 29-B3	C4 26-B4	C5 29-B2	C6 22-D3	C7 41-C6	C8 29-B2	C9 29-B2	C10 21-D3	C11 29-B2	C12 36-A7	C13 29-B3	C14 41-C6	C15 20-D3	C16 39-D6	C17 32-B2	C18 41-B6	C19 18-D7	C20 36-A4	C21 36-A4	C22 36-A4	C23 36-A4	C24 36-A5	C25 17-C5	C26 36-C7	C27 36-C7	C28 36-D7	C29 32-C3	C30 41-A6	C31 32-B5	C32 39-C7	C33 39-D7	C34 39-C7	C35 39-C7	C36 39-B1	C37 25-C7	C38 25-D7	C39 32-C5	C40 15-C3	C41 38-B4	C42 17-B4	C43 38-B4	C44 38-B4	C45 17-B4	C46 17-D7	C47 29-C3	C48 29-C3	C49 39-B4	C50 39-B4	C51 39-B4	C52 39-B4	C53 39-B4	C54 39-B4	C55 39-A4	C56 39-B4	C57 39-B4	C58 39-B4	C59 39-D6	C60 39-D6	C61 39-C6	C62 39-C6	C63 39-D6	C64 32-C7	C65 32-B7	C66 32-B6	C67 32-B6	C68 32-D6	C69 32-D6	C70 32-B6	C71 32-D6	C80 24-B8	C81 34-B8	C82 24-B8	C83 24-C7	C84 24-C7	C85 34-B8	C86 35-A4	C87 35-A6	C88 22-D1	C89 22-D1	C90 21-D3	C91 21-D3	C92 20-D3	C93 20-D3	C94 18-D8	C95 39-A1	C96 39-B1	C97 25-A7	C98 25-B7	C99 25-A6	C100 32-B5	C101 22-C5	C104 27-D3	C105 34-B1	C106 41-B7	C107 34-A1	C108 34-A1	C109 34-B1	C110 34-A2	C111 34-B7	C112 34-B7	C113 25-C5	C114 26-B4	C115 41-C7	C116 22-D1	C117 22-A3	C118 22-A3	C119 21-D3	C120 21-A5	C121 21-A5	C122 20-D1	C123 20-B5	C124 20-B5	C125 20-D1	C126 20-D1	C127 18-D2	C128 18-D3	C129 18-D2	C130 33-C3	C131 18-D1	C132 37-B5	C133 39-A2	C134 39-B2	C135 31-A2	C136 31-A2	C137 31-A2	C142 27-B6	C144 27-B5	C146 27-D3	C147 27-D2	C148 34-B1	C149 34-A2	C150 34-B2	C151 34-A2	C152 34-B2	C153 34-A2	C154 34-A2	C155 34-A2	C156 34-B1	C157 34-B2	C158 41-B7	C159 34-B7	C160 41-C6	C161 25-A5	C162 30-B8	C163 22-D3	C164 22-D5	C165 22-D5	C166 21-D2	C167 21-D2	C168 21-D1	C169 21-D1	C170 20-D2	C171 20-D2	C172 18-D2	C173 18-D3	C174 18-D3	C175 18-D4	C176 18-D2	C177 18-D2	C178 18-D3	C179 31-A3	C180 31-A3	C181 31-A2	C182 31-B5	C183 31-B5	C184 31-B3	C186 23-A2	C187 23-D6	C188 27-B5	C189 26-A7	C190 27-D2	C193 25-C4	C194 25-C5	C195 25-D5	C196 25-C5	C197 25-B5	C198 25-A5	C199 30-B7	C200 22-D3	C201 22-D2	C202 22-D2	C203 21-D2	C204 21-D2	C205 21-D4	C206 21-D4	C207 21-D4	C208 20-D1	C209 20-D2	C210 20-D2	C211 20-D4	C212 20-D4	C213 18-D3	C214 18-D1	C215 18-D4	C216 18-D5	C217 18-D1	C218 18-D7	C219 18-D7	C220 18-D3	C221 31-A3	C222 31-A4	C223 31-A3	C224 31-A3	C225 8-B4	C226 8-B3	C227 11-B5	C228 11-B5	C229 12-C5	C230 11-B6	C231 11-B5	C232 41-C7	C233 16-A3	C234 22-D2	C235 21-D4	C236 21-D4	C237 20-D4	C238 7-B2	C239 7-B2	C240 7-B2	C241 7-B2	C242 7-B1	C243 7-B4	C244 7-B4	C245 23-D7	C246 6-A4	C247 5-A4	C248 6-A3	C249 6-A2	C250 5-A6	C251 5-A6	C252 5-A7	C253 11-B2	C254 11-B2	C255 10-D5	C256 11-B2	C257 11-B2	C258 16-B3	C259 16-B3	C260 16-B4	C261 22-D2	C262 41-C7	C263 21-D4	C264 41-C6	C265 41-B7	C266 20-D4	C267 19-D5	C268 3-A6	C269 18-D1	C270 9-A3	C271 9-D5	C272 9-A6	C273 6-A5	C274 6-A5	C275 6-A1	C276 6-A2	C277 6-A5	C278 6-A3	C279 6-A2	C280 6-A2	C281 6-A1	C282 6-A5	C283 10-D5	C284 11-C2	C285 11-C2	C286 10-D5	C287 10-D5	C288 11-C2	C289 11-C2	C290 16-A4	C291 16-B4	C292 36-A5	C293 22-D3	C294 36-A5	C295 21-D3	C296 20-D3	C297 17-A6	C298 7-A4	C299 7-A4	C300 7-A6	C301 7-A3	C302 7-A4	C303 7-A5	C304 15-C5	C305 15-C5	C306 11-B5	C307 11-B5	C308 11-B6	C309 11-B5	C311 24-C3	C314 17-A7	C315 41-C6	C317 3-A6	C318 3-A4	C319 7-A7	C320 5-C5	C321 5-C5	C322 5-C4	C323 5-C4	C324 15-A4	C325 15-A4	C326 17-C6	C330 41-C6	C331 3-A6	C332 4-B7	C333 4-B7	C334 4-B7	C335 4-B7	C336 4-B5	C337 3-A7	C338 41-B6	C339 4-B3	C340 41-C8	C341 40-A4	C342 41-B8	C343 40-B4	C344 40-B5	C345 40-C6	C346 40-B5	C347 40-C5	C348 41-C6	C349 24-B4	C350 24-B4	C351 24-B4	C352 41-B6	C353 41-B6	C400 18-D6	C401 34-B3	C402 28-C3	C403 38-B2	C404 25-D7	C405 25-D7	C410 39-C7	C411 39-D7	C412 39-C7	C413 39-C7	C414 36-C2	C415 36-C3	C416 36-D2	C417 36-D3	C418 36-D3	C419 36-D3	C420 38-C7	C421 38-C7	C422 38-C7	C423 36-C4	C424 38-B7	C425 38-B7	C426 36-C3	C427 36-A4	C428 38-B7	C429 37-B7	C430 37-B7	C431 37-C7	C432 37-C7	C433 37-B6	C434 37-C7	C435 36-A7	C436 36-A6	C437 36-A6	C438 36-A6	C439 36-A6	C440 36-A7	C441 26-B4	C442 34-A1	C443 34-A2	C444 41-C7	C445 34-A1	C446 34-B2	C447 34-B1	C448 34-A1	C449 34-A1	C450 34-B1	C451 28-C5	C452 28-B8	C453 28-C4	C454 28-C2	C455 28-C2	C456 28-C2	C457 28-C3	C458 28-C4	C459 28-C8	C460 28-C3	C461 31-C6	C462 31-C6	C463 31-C6	C464 31-C6	C465 31-C6	C466 31-C6	C467 31-C6	C468 31-C6	C469 31-C6	C470 32-B5	C471 31-C7	C472 31-C7	C473 39-B3	C474 39-A3	C475 38-C2	C476 38-C2	C477 38-C2	C478 40-B3	C479 40-A3	C480 36-A3	C481 36-A3	C482 18-D7	C483 18-D8	C484 20-D3	C485 21-D4	C486 22-D1	C487 26-B4	C488 25-A4	C489 25-C4	C490 25-A4	C491 25-A5	C492 25-A5	C493 34-B2	C494 34-A2	C495 34-B3	C496 34-B7	C497 34-B8	C498 27-D3	C499 27-D2	C500 31-A3	C501 39-B3	C502 39-B2	C503 39-B3	C504 39-B3	C505 39-B2	C506 39-A3	C507 39-A2	C508 37-B5	C509 37-B5	C510 18-B5	C511 18-B4	C512 18-D2	C513 18-D4	C514 20-D2	C515 20-D3	C516 21-D1	C517 21-D1	C518 21-D2	C519 21-D4	C520 22-D5	C521 22-D5	C522 22-D4	C523 26-D3	C524 41-C7	C525 26-B4	C526 41-B6	C527 25-A4	C528 14-A8	C530 27-A3	C531 27-A3	C532 23-A2	C533 31-D3	C534 31-D3	C541 10-A4	C542 33-C2	C543 18-D5	C544 18-D2	C545 18-D4	C546 18-D4	C547 18-D2	C548 18-D4	C549 20-D2	C550 20-D2	C551 20-D2	C552 21-D2	C553 22-D4	C554 22-D4	C555 22-D4	C556 14-C1	C557 14-C1	C558 13-A7	C559 13-D1	C560 13-A8	C561 23-D3	C562 23-A5	C563 23-D3	C564 23-D2	C565 23-D2	C566 23-A2	C567 23-D2	C568 23-A1	C569 23-A1	C570 23-A2	C571 23-D1	C572 23-A2	C573 23-A2	C574 23-A2	C575 8-B4	C576 8-B3	C577 8-B1	C578 8-B3	C579 8-B3	C580 8-C4	C581 19-D4	C582 19-A1	C583 19-D1	C584 19-B1	C585 19-A1	C586 19-D1	C587 18-D4	C588 18-D4	C589 20-D2	C590 20-D2	C591 21-D1	C592 21-D1	C593 21-D2	C594 22-D4	C595 22-D4	C596 22-D4	C597 22-D4	C598 30-B6	C600 30-B7	C601 14-A7	C602 14-A1	C603 13-A7	C604 13-D1	C605 12-C5	C606 12-C5	C607 12-C5	C608 12-C5	C609 23-D7	C610 5-B5	C611 23-C7	C612 23-D3	C613 23-D1	C614 23-D2	C615 23-D1	C616 23-A2	C617 8-C4	C618 8-C5	C619 19-A1	C620 19-B1	C621 19-D2	C622 19-D3	C623 19-D3	C624 19-D2	C625 19-D3	C626 19-A2	C627 19-A2	C628 19-A2	C629 19-A2	C630 19-D4	C631 19-D1	C632 19-D1	C633 19-B1	C634 18-D8	C635 20-D2	C636 22-D2	C637 30-C7	C638 30-B5	C639 14-A7	C640 14-A1	C641 13-A7	C642 13-B1	C643 12-C2	C644 12-C2	C645 12-C2	C646 12-C2	C647 5-A6	C648 5-A6	C649 5-A4	C650 5-A6	C651 5-A5	C652 5-B4	C653 5-B6	C654 9-D6	C655 9-D6	C656 9-D7	C657 9-D7	C658 9-D7	C659 9-D7	C660 9-D7	C661 9-A7	C662 9-D7	C663 9-D6	C664 9-D6	C665 19-D2	C666 19-B2	C667 19-A2	C668 19-A2	C669 19-B2	C670 19-A1	C671 19-A1	C672 19-D4	C673 19-D5	C674 19-D4	C675 19-D3	C676 19-D3	C677 19-A2	C678 19-D4	C679 19-B2	C680 19-D3	C681 19-A2	C682 19-D2	C683 19-A1	C684 19-B1	C685 19-D1	C686 19-A1	C687 7-B4</

1	2	3	4	5	6	7	8		
A	REFERENCE DESIGNATOR LOCATIONS								
	R278 15-D3	R489 28-A6	R614 27-C3	R730 8-C4	R823 9-B2	R916 24-A4	R1016 3-C2		
	R280 15-C3	R490 28-B2	R615 27-C7	R731 8-C4	R824 9-B2	R917 24-A4	R1017 3-C2		
	R281 15-D2	R491 28-B2	R616 28-C6	R732 8-B2	R825 9-A5	R918 36-A4	R1018 3-C2		
	R282 15-D2	R509 39-D6	R624 31-D5	R733 19-C5	R826 9-B2	R919 16-A3	R1019 3-C2		
	R283 5-A6	R510 39-B3	R628 31-D5	R734 19-C6	R827 9-B7	R920 12-B6	R1020 3-C1		
	R284 17-C7	R511 39-B3	R629 31-D6	R735 19-C5	R828 9-B7	R921 12-B7	R1021 3-C1		
	R285 17-B4	R512 39-A3	R630 31-B5	R736 19-C6	R829 19-B6	R922 12-B5	R1022 3-C2		
	R286 17-D6	R513 39-C3	R635 33-C5	R737 19-C5	R830 19-D6	R923 6-C6	R1023 3-C2		
	R287 17-D7	R514 39-A3	R636 33-C4	R738 19-C5	R831 7-C2	R924 6-C7	R1024 3-D5		
B	R288 39-B4	R515 39-A3	R637 33-B4	R739 19-C5	R832 7-C2	R925 6-C7	R1025 3-D4		
	R289 39-B4	R516 39-A3	R638 33-C2	R740 19-D6	R833 7-C2	R926 15-A5	R1026 17-A6		
	R290 29-D2	R517 39-B3	R639 33-B2	R741 19-D5	R834 7-C2	R927 15-A4	R1030 30-A3		
	R291 29-D3	R518 25-A6	R640 23-B3	R742 19-D5	R835 7-C6	R928 7-B6	R1031 24-C5		
	R292 29-D2	R519 25-B6	R641 23-A3	R743 19-C3	R836 7-C5	R929 7-B5	R1032 24-C6		
	R293 29-D2	R520 39-A2	R642 23-D2	R744 19-B2	R837 7-C3	R930 7-B5	R1033 24-C6		
	R318 24-B6	R521 39-B2	R646 23-D2	R745 18-C5	R838 7-C3	R931 7-A4	R1034 24-C5		
	R320 24-A6	R522 36-A2	R647 23-D2	R746 20-C4	R839 6-C2	R932 7-B4	R1035 24-C4		
	R321 24-A6	R523 36-A2	R649 31-C5	R747 30-A2	R840 6-B2	R933 3-C7	R1036 24-C5		
	R345 24-C2	R524 18-B7	R650 31-D6	R748 30-A7	R841 6-C8	R934 3-B7	R1037 24-C5		
C	R400 35-B3	R525 18-A4	R651 31-C5	R749 30-B5	R842 6-A3	R935 3-B7	R1038 24-C3		
	R401 35-B3	R526 18-A4	R652 31-A4	R750 11-B7	R843 6-A2	R936 3-B8	R1039 24-B5		
	R402 35-B5	R527 18-A5	R655 31-D5	R751 12-D3	R844 6-A2	R937 3-C2	R1040 40-B3		
	R407 39-C7	R528 18-B5	R656 31-C5	R752 11-B7	R845 6-B2	R938 3-B8	R1041 40-B3		
	R408 36-C4	R529 20-A7	R657 31-C6	R753 12-D2	R846 6-B2	R939 3-B6	R1042 40-B3		
	R409 36-D4	R530 20-A5	R658 31-C6	R754 12-C4	R847 11-B5	R940 3-B7	R1043 40-A3		
	R410 36-C8	R531 20-B5	R659 31-C7	R755 12-C2	R848 11-C2	R941 3-B7	R1044 40-A4		
	R411 36-A8	R532 21-A7	R660 31-C7	R756 12-D6	R849 11-C2	R946 24-B2	R1045 40-B5		
	R412 36-A7	R533 21-B4	R661 31-D4	R757 5-B6	R850 11-B2	R947 24-A3	R1046 40-B5		
	R413 36-A7	R534 21-B5	R662 10-B6	R758 6-B7	R851 6-B2	R948 12-B3	R1047 16-D5		
D	R414 30-B3	R535 22-A5	R663 10-B6	R759 6-B6	R852 6-B2	R949 12-B2	R1048 16-D6		
	R415 29-B6	R536 22-B4	R664 10-A5	R760 6-B7	R853 9-D2	R950 12-B4	R1049 16-D4		
	R416 30-C2	R537 26-C3	R665 10-A4	R761 23-C7	R854 11-A5	R951 12-B6	R1050 16-C3		
	R418 29-C7	R538 26-C5	R666 10-A4	R762 23-C7	R855 9-C2	R952 12-B3	R1051 16-C3		
	R419 22-B5	R539 26-C3	R667 10-A4	R763 5-B5	R856 9-D2	R953 6-C7	R1052 4-C6		
	R420 29-C6	R540 26-C2	R668 10-B4	R764 5-B4	R857 9-C7	R954 16-C5	R1053 4-D7		
	R421 21-B6	R541 35-B7	R669 10-B3	R765 23-A4	R858 9-B7	R955 16-C5	R1054 4-B2		
	R422 29-B6	R542 35-C7	R670 10-B3	R766 5-B4	R859 9-C7	R956 15-B4	R1055 4-B2		
	R423 20-B6	R543 25-C3	R671 18-B4	R767 23-B7	R860 9-B7	R957 15-B4	R1056 4-B2		
A	R424 29-B3	R544 25-C3	R672 18-C4	R768 23-B7	R861 9-C7	R958 15-B4	R1057 4-C2		
	R425 29-B3	R545 25-C3	R673 18-C4	R769 23-B7	R862 9-A3	R959 15-B4	R1058 4-B3		
	R426 35-A4	R546 25-C3	R674 20-B7	R770 23-B6	R863 9-A3	R960 15-B3	R1059 4-C6		
	R427 35-A3	R547 25-B3	R675 20-C2	R771 23-B7	R864 9-C7	R961 7-B6	R1060 3-A3		
	R428 35-B6	R548 25-B3	R676 20-B7	R772 23-B6	R865 9-C7	R962 7-B5	R1061 16-A5		
	R429 35-A5	R549 25-B3	R677 20-B7	R773 23-B6	R866 9-D4	R963 7-B5	R1062 16-B4		
	R430 34-A4	R551 34-C3	R678 14-D5	R774 23-B6	R867 9-C7	R964 5-C5	R1063 16-B5		
	R431 34-A4	R552 34-D2	R679 14-D5	R775 23-B6	R868 19-D5	R965 5-C5	R1064 16-B6		
	R432 28-B6	R553 34-C3	R680 14-D2	R776 23-B7	R869 19-D5	R966 5-C4	R1065 17-B4		
	R433 28-B6	R554 27-D4	R681 14-D2	R777 23-B7	R870 7-D3	R967 5-C4	R1066 16-B6		
B	R434 28-B4	R555 27-B4	R682 13-D5	R778 23-B7	R871 7-C6	R968 3-B7	R1067 24-D7		
	R435 28-C4	R556 27-C3	R683 13-D5	R779 23-B7	R872 7-C5	R969 3-C6	R1072 4-A3		
	R436 28-B6	R557 27-A3	R684 13-D2	R780 23-B6	R873 7-C5	R970 3-C2	R1073 24-D7		
	R437 28-B4	R559 27-D4	R685 13-D2	R781 8-B6	R874 7-C3	R971 3-C3	R1074 4-A3		
	R438 28-C6	R560 27-B2	R686 12-D5	R782 8-B6	R875 7-C3	R972 3-B7	R1075 4-A5		
	R439 28-C3	R561 27-C2	R687 12-C7	R783 23-C7	R876 7-C3	R973 3-C2			
	R449 25-C6	R562 27-B2	R688 26-B7	R784 9-B3	R877 21-A3	R974 3-D5			
	R450 25-D6	R563 27-B2	R689 26-B6	R785 8-C4	R878 6-C5	R975 3-C2			
	R451 39-B2	R564 27-B7	R690 26-B6	R786 19-C5	R879 6-C7	R976 17-A7			
	R452 39-D7	R565 27-B2	R691 23-B2	R787 19-C6	R880 6-D5	R977 17-A5			
C	R453 39-C7	R566 27-B4	R692 23-D4	R788 19-D6	R881 6-D6	R978 17-B4			
	R454 39-C7	R567 27-B3	R693 23-D2	R789 19-C6	R882 6-D7	R979 17-B6			
	R455 39-B2	R568 27-A3	R694 19-D5	R790 19-D5	R883 6-D7	R980 17-B4			
	R456 38-C6	R569 27-A2	R695 23-C2	R791 19-D6	R884 9-C2	R981 17-A4			
	R457 38-C6	R570 27-D3	R696 23-D2	R792 19-D6	R885 9-A7	R982 17-A5			
	R458 38-B6	R571 27-B7	R697 23-D2	R793 19-C3	R886 9-B6	R983 24-C3			
	R459 38-C6	R572 27-C7	R698 23-D2	R794 19-D6	R887 11-B2	R984 24-C2			
	R460 38-B6	R573 27-B6	R699 23-B6	R795 19-B3	R888 11-A2	R985 24-B2			
	R461 38-B6	R574 27-A3	R700 23-B7	R796 19-C3	R889 7-C5	R986 24-C3			
	R462 37-B6	R575 27-C7	R701 8-A2	R797 19-C3	R890 7-C3	R987 24-B1			
D	R463 37-B6	R576 27-C7	R702 8-B2	R798 19-C3	R891 12-B5	R988 24-C3			
	R464 37-B6	R580 32-A7	R703 10-B5	R799 19-C3	R892 6-C7	R989 15-B6			
	R467 37-C6	R581 32-C7	R704 10-B6	R800 19-B3	R893 6-C6	R990 40-C5			
	R468 37-C6	R586 31-A4	R705 10-B5	R801 19-D6	R894 6-D6	R991 40-C4			
	R470 29-C6	R589 37-B5	R706 18-B5	R802 7-C4	R895 6-C7	R992 16-C5			
	R471 29-C5	R591 37-A3	R707 18-B5	R803 7-C5	R896 6-D7	R993 16-C5			
	R472 29-C2	R592 37-B5	R708 30-A2	R804 7-B4	R897 6-D7	R994 16-C5			
	R474 29-B2	R593 33-C6	R709 29-B7	R805 7-C3	R898 15-C4	R995 16-D5			
	R475 29-B3	R594 33-C6	R710 30-A7	R806 30-B5	R899 7-B5	R1000 16-D2			
	R476 30-B2	R595 37-A5	R711 29-B7	R807 30-B4	R900 7-B7	R1001 16-D2			
A	R477 29-C7	R597 37-A3	R712 30-B7	R808 16-A2	R901 7-A7	R1002 16-D2			
	R478 35-B2	R598 33-A4	R713 12-D6	R809 12-D3	R902 3-B6	R1003 16-C2			
	R479 35-C7	R599 33-B2	R714 12-C5	R810 5-B6	R903 3-B6	R1004 16-D3			
	R480 35-C2	R600 33-B3	R715 26-B6	R811 5-B5	R904 3-B7	R1005 7-B5			
	R481 35-B7	R601 33-B3	R716 23-C2	R812 6-B7	R905 3-B7	R1006 3-D6			
	R482 35-B7	R602 33-A3	R717 23-C2	R813 6-B7	R906 3-B6	R1007 3-D6			
	R483 35-C7	R603 33-B3	R718 23-C2	R814 6-B7	R907 3-B7	R1008 3-C2			
	R484 34-D4	R604 18-A4	R719 23-C2	R815 6-B7	R908 17-B7	R1009 3-D3			
	R485 34-C2	R605 18-B4	R720 23-C2	R816 6-B7	R909 17-B7	R1010 3-D3			
	R486 28-B2	R606 26-C4	R721 23-D2	R817 6-B7	R910 3-C3	R1011 3-C3			
B	R487 28-C2	R607 26-D2	R722 23-D2	R818 9-B2	R911 24-A7	R1012 3-B6			
	R488 27-C4	R608 26-D2	R723 23-D2	R819 9-B2	R912 24-A7	R1013 3-B6			
		R613 27-C2	R724 23-D2	R820 9-C2	R913 17-B7	R1014 3-C2			
			R725 23-D2	R821 9-C2	R914 24-B6	R1015 3-D5			
			R726 23-D2	R822 9-C2	R915 24-A5				
			R727 23-D2						
			R728 8-B4						
			R729 8-B6						
NOTICE OF PROPRIETARY PROPERTY THE INFORMATION CONTAINED HEREIN IS THE PROPRIETARY PROPERTY OF APPLE COMPUTER, INC. THE POSSESSOR AGREES TO THE FOLLOWING (I) TO MAINTAIN THE DOCUMENT IN CONFIDENCE (II) NOT TO REPRODUCE OR COPY IT (III) NOT TO REVEAL OR PUBLISH IT IN WHOLE OR PART							SIZE D	DRAWING NUMBER 051-0777	REV. C
ECS CAD GENERATED APPLE CONFIDENTIAL							SCALE NONE	SHT 43 OF 43	
1	2	3	4	5	6	7	8		

12345678

A

B

C

D

12345678

PROTO REVISION HISTORY

PROTO1 - 6 MAY 98
FEATURE CHANGES
- ELIMINATE FRONT PANEL HEADPHONE AND ASSOCIATED CIRCUITRY
- REMOVE PROVISION FOR FRONT PANEL FIREWIRE
- REMOVE INTERNAL USB PORT
- REMOVE 2 EXTERNAL USB PORTS
- REMOVE SECOND ULTRA-ATA PORT
- REMOVE RCA LINE IN/OUT CONNECTOR AND CIRCUITRY
- ADD BI-COLOR LED ON FRONT PANEL BOARD AND ASSOCIATED CIRCUITRY ON MLB
- INTEGRATE IRDA AND FPB ON NEW COMBO IRDA/FPB BOARD

PROTO1 BUG LIST FROM RADAR:
TAG #1 - MOVED USB PCISEL BIT TO PCIA222
TAG #2 - MOVED PADDINGTON PCISEL BIT TO PCIA21
TAG #3 - SET Y3 SET TO STUFF (STUFFING ERROR)
TAG #4 - REVERSE BURGUNDY/PADDINGTON CLOCK CHIP'S XI/XO BITS (SYMBOL ERROR)
TAG #5 - CORRECT PCI SYSTEM CLOCK CONTENTION (STUFFING ERROR)
TAG #6 - CORRECT POWER TO GROUND SHORT UNDER DAC (PCB ERROR)
TAG #7 - MAKE EXTERNAL CLOCK SOURCE RESISTOR NO-STUFF (STUFFING ERROR)
TAG #8 - CORRECT BOOT ROM MSB ADDRESS ERROR
TAG #9 - REMOVE PIN 20 ON UATA AND IDE CONNECTORS (STUFFING ERROR)
TAG #10 - MAKE POWERON* TO +5TRICKLE A NO-STUFF
TAG #11 - CORRECT NON-MONTONIC EDGES ON SYSRST* AND CUDANMI*
TAG #12 - CORRECTED CAPS MIS-LOAD WITH RESISTORS (STUFFING ERROR)
TAG #13 - L2TSTCLK NOW PULLED LOW (STUFFING ERROR)
TAG #14 - CHANGED VIO PINS FOR DEC BRIDGE
TAG #15 - CORRECTED BR1DITY* FLOATING BUS REQUEST (STUFFING ERROR)
TAG #16 - CONNECTED SLOTRST* TO SOUTH PCI SLOTS
TAG #17 - CORRECTED SHORTED PCI SLOTS PCIDSEL BITS
TAG #18 - CORRECTED S5 MIS-WIRE (CUDA SOFT-START)
TAG #19 - CORRECTED PFW TO +5V PULL-UP RESISTOR VALUE
TAG #20 - CORRECTED CUDA SIGNAL PULL-UP VALUE ERROR (STUFFING ERROR)
TAG #21 - STUFFED L16 FOR USB POWER (STUFFING ERROR)
TAG #22 - CORRECTED R888 WRONG VALUE - WAS CRASHING ON RESTART
TAG #23 - CORRECTED +5VTRICKLE EXCESSIVE LOAD (USING TRANSISTOR)
TAG #24 - PULLED-UP SPCIAK64*
TAG #25 - COMBINED IRDA AND FPB CONNECTORS - CORRECTS IRDA WIRING ERROR
TAG #26 - ADDED SEPERATE PULL-DOWN RESISTORS FOR PROPER CONFIGURATION
TAG #27 - (de-assigned)
TAG #28 - FIXES IN TAG #26 CORRECT THIS CONFIGURATION ERROR
TAG #29 - FIXES IN TAG #26 CORRECT THIS CONFIGURATION ERROR
TAG #30 - ADDED P/Ds TO ASIC1MS & ASIC2CLK, SCANPCITMS & SCANPCITCLK
TAG #31 - FIREWIRE BUS HOLDERS NEED +3.3V & ASSORT. VALUE CHANGES
TAG #32 - 400MHZ IBM INTERPOSER DOES NOT FUNCTION
TAG #33 - 66MHZ PCI SLOT CLOCK DELAY STUFFONG ERROR

NO TAG #1 - MOVE PCI EXTRA TRACE LENGTHS TO BETWEEN J10 AND J11
NO TAG #2 - INCREASE TRACE WIDTH ON BOTH SIDES OF R43
NO TAG #3 - CORRECTED USE OF 0646U VS. 0646U2 DESIGN ERROR
NO TAG #4 - CHANGED DATA CAPS TO 2KV = THEN CHANGE BACK TO ORIGINAL
NO TAG #5 - MAKE 100MPBS VEL AND 10MBPS GRN (SCHEMATIC AND PCB CHANGE)
NO TAG #6 - ADDED SUPPORT FOR +5V VCC FLASH ROM
NO TAG #7 - ADDED RESISTORS TO USB POWER-ON FEEDBACK CIRCUIT (OVL*)
NO TAG #8 - CHANGED GATED CLOCKS-II'S RESET TO ONE WITH A +3.3V SWING
NO TAG #9 - CHANGE ENET CONNECTOR MOUNTING HOLES TO PLATED-THRU
NO TAG #10 - WATCH FOR FAB HOUSE CREATED SHORTS!
NO TAG #11 - MOVE L98 TO TOP SIDE OF PCB
NO TAG #12 - CHANGED PID BITS TO MATCH MSB-LSB
NO TAG #13 - REMOVE PLANE POUR UNDER ANALOG ETHERNET AREA
NO TAG #14 - ADD SERIES RESISTOR TO CUDA'S RESET INPUT
NO TAG #15 - CHANGED TO SG500C WHICH REQUIRED A PINOUT REVISION
NO TAG #16 - ADDED STUFFING OPTIONS FOR FAN SPEED CONTROL
NO TAG #17 - GROUND STITCHING CAPS ADDED FOR 3 SIDES OF PCB
NO TAG #18 - INCORPORATE MOUNTING AND TOOLING HOLE CHANGES
NO TAG #19 - VERIFY GEOMETRY OF U34, 310S0008
NO TAG #20 - ENSURE VREG TAB SIZE PADS ARE INCREASED
NO TAG #21 - YR1 REFERENCE DESIGNATOR CHANGED
NO TAG #22 - PADDINGTON FIREWIRE READ BIT MOVED TO BIT 1
NO TAG #23 - ADDED AMP MIC SENSE SIGNAL FOR S/W GAIN CONTROL
NO TAG #24 - ADDED PUs TO GRMA(4:0) AND GRSDBA(0)
NO TAG #25 - ADD DOUBLE VIAS ON LOW FREQUENCY CAPS
NO TAG #26 - AUDIO VALUE CHANGES TO HEADPHONE CIRCUIT
NO TAG #27 - MOVE HEADPHONE AMP AWAY FROM 66MHZ CLOCKS

12345678

A

B

C

D

12345678

EVT REVISION HISTORY

EVTA - 22JUNE98
EVTA BUG LIST FROM RADAR:
TAG #1 - U34 HAS WRONG PART LOADED - NO SCHEMATIC CHANGE
TAG #2 - USB CHIP IS OPTI BUT SHOULD BE LUCENT
TAG #3 - ROMS BOTTOM BOOT BLOCK NOT WRITABLE
TAG #4 - UATA AND IDE CONNECTORS ARE SWAPPED
TAG #5 - MODEM CONNECTOR MAY BE REVERSED
TAG #6 - MEMORY PROFILE RESISTORS SHOULD NOT BE LOADED
TAG #7 - CLOCK SERIES TERMINATIONS NEED VALUE CHANGES
TAG #8 - CLOCK DELAY MAZES NEED STUFFING CHANGES
TAG #9 - FIREWIRE SCLKS NOMIMAL VOLTAGE NOT CENTERED
TAG #10 - LUCENT USB CHIP CAUSES SHORT BETWEEN +3.3V AND +5V
TAG #11 - UATA/IDE DRIVE SIGNALS HAVE POOR QUALITY
TAG #12 - CUDA P/D MISSING
TAG #13 - UATA SET TO RAID MODE
TAG #14 - ASCITRST* AND SCANPCITRST* HAVE BAD LEVELS
TAG #15 - ENET LEDS DO NOT OPERATE CORRECTLY
TAG #16 - VR2-1 GROUND (CONNECTION AND TRACE SIZE) ERROR
TAG #17 - UATA POWERED FROM +3.3V SHOULD BE FROM +5V
TAG #18 - ANTIPOBBIAS CIRCUIT MISSING
TAG #19 - MISSING P/U ON BURGUNDY POWERON
TAG #20 - CPU CORE VOLTAGE REGULATOR CIRCUIT HAS GLITCHES ON FEEDBACK LOOP
TAG #21 - HEADPHONE CAPS ARE WRONG VALUE
TAG #22 - IRDA CLOCK AND HANDSHAKE SIGNALS REVERSED
TAG #23 - POWER PROTECTION DIODES SHOULD BE STUFFED
TAG #24 - OPTI USB CONTROLLER POWEROK INPUTS WIRED INCORRECTLY
TAG #25 - DVD INPUT CAPS SHOULD BE 1UF NPO X7R
TAG #26 - SYSTEM POWERS-UP WHEN INSERTING AC/DC POWER CABLE
TAG #27 - USB SWITCH REPORTS OVL WHEN DEVICE IS INSERTED

NO TAG #1 - SILK SCREEN NEEDS ENHANCEMENT
NO TAG #2 - THERE ARE 2 NETNAME SHORTS

EVTB - 8JULY98
EVTB BUG LIST FROM RADAR:
TAG #1 - ANTIPOBBIAS CIRCUIT MISSING
TAG #2 - BURGUNDY ENABLE NOT PULLED-UP
TAG #3 - HEADPHONE CAPS ARE WRONG VALUE
TAG #4 - CPU CORE VOLTAGE REGULATOR CIRCUIT HAS GLITCHES ON FEEDBACK LOOP
TAG #5 - POWER PROTECTION DIODES SHOULD BE STUFFED
TAG #6 - OPTI USB CONTROLLER POWEROK INPUTS WIRED INCORRECTLY
TAG #7 - IRDA CLOCK AND HANDSHAKE SIGNALS REVERSED
TAG #8 - DVD INPUT CAPS SHOULD BE 1UF NPO X7R
TAG #9 - SYSTEM POWERS-UP WHEN INSERTING AC/DC POWER CABLE
TAG #10 - USB CHIP REPORTS OVL WHEN DEVICE IS INSERTED
TAG #11 - DVD DAC IS WRONG TYPE FOR C-QUEE CHIP
TAG #12 - PCI ARBITOR SHOULD NT BE PART OF SCAN CHAIN
TAG #13 - FLASH ROM'S BOTTOM BOOT BLOCK IS STILL WRITABLE
TAG #14 - IRDA TO CHASSIS/LOGIC GND CAPS SHOULD NOT BE STUFFED
TAG #15 - MODEM POWER-UP SIGNAL CONNECTED INCORRECTLY W/ NO PU
TAG #16 - BURGUNDY SENSE CAPS ARE WRONG VALUE
TAG #17 - DAC HAS NO PD RESISTORS ON IT'S INPUTS
TAG #18 - HEADPHONE SERIES RESISTORS ARE WRONG VALUE
TAG #19 - HEADPHONE OPAMP IS WRONG VALUE
TAG #20 - SPEAKER AMP EMI CAPS ARE WRONG VALUE
TAG #21 - ULTRA-ATA DSTROBE* HAS BAD TIMING AND HIGH LEVELS
TAG #22 - SG500 SHOULD BE SHOULD BE CHANGED TO USE THE REV D PART
TAG #23 - ULTRA-ATA DSTROBE* STILL HAS BAD TIMING (TAKE 2)
TAG #24 - CORE REGULATOR LESS STABLE THAN EXPECTED
TAG #25 - USB'S OSCILLATOR IS UNSTABLE
TAG #26 - 18.432MHZ OSCILLATOR IS UNSTABLE
TAG #27 - SDRAM ADDRESS BUFFERS NOT INITIALIZED PROPERLY
TAG #28 - SYSTEM POWERS-UP WHEN INSERTING AC/DC POWER CABLE (TAKE 2)
TAG #29 - ULTRA-ATA DSTROBE* STILL HAS BAD TIMING (TAKE 3)

NO TAG #1 - SILK SCREEN PART LABELS IN CORRECT LOCATION AND IN BIGGER FONT
NO TAG #2 - EMI SHIELD TOUCHES F1
NO TAG #3 - 66MHZ PCI CLOCKS NEED LENGTH CHANGES
NO TAG #4 - BGA PINS NEED SOLDER MASK FOR PRODUCTION
NO TAG #5 - 33MHZ PCI SIGNALS AND SOME PCI CLOCKS NEED NET LENGTH CONSTRAINTS
NO TAG #6 - IRDA OUTPUT SIGNALS NEED SERIES TERMINATION
NO TAG #7 - ENET CONNECTOR SHOULD BE CHANGED TO EXCLUDE LEDS
NO TAG #8 - H/W AND PCB GROUPS HAVING DIFFICULTIES MAINTAINING NET LENGTH FILES
NO TAG #9 - PCI SLOT'S REQ'S AND INTS ARE SHORTED ACROSS ALL SLOTS
NO TAG #10 - 1/O EMI SHIELD MOUNT POST IS TOO CLOSE TO L98
NO TAG #11 - SYSRST* AND NMISW* HAVE NON-MONOTONIX EDGES

12345678

A

B

C

D

12345678

DVT REVISION HISTORY

DVT - 4SEPT98
DVT BUG LIST FROM RADAR:
TAG #1 - UNCONNECTED INPUT PINS ON CHIP USED FOR RESET AND NMI
TAG #2 - GATED CLOCKS-II'S SINGLE-CYCLE GRANTS NOT ALWAYS RECOGNIZED
TAG #3 - NMI / FPB SWITCH DOES NOT FUNCTION
TAG #4 - SOUND RECORDING FAILS WITH PARTIAL DATA
TAG #5 - INPUT CHANNEL CROSSTALK SPEC NOT MET WITH COMPONENT VALUES
TAG #6 - HIGH SOFT ERROR RATE ON ATA(4) INTERFACE
TAG #7 - FPB'S POWER SWITCH SHOULD CONNECTED TO 'CHASSIS SWITCH'
TAG #8 - SDRAM FAILURES CAUSED FROM TOO SLOW A RISE TIME
TAG #9 - SDRAM SDBA(1) STILL HAS TOO SLOW A RISE TIME UNDER HEAVY LOADS

NO TAG #1 - MODEM AND F/W CONNECTORS SHOULD HAVE PIN-1 INDICATOR
NO TAG #2 - SOME CAPS ARE TOO CLOSE TO MEMORY DIMM CONNECTORS
NO TAG #3 - SOME VIA HOLES LOCATED AT BGA ARE NOT MASKED BY SILKSCREEN
NO TAG #4 - SOLDER BALLS AT LOCATION J25 AFTER REFLOW
NO TAG #5 - USB PORT ORDERING DOES NOT AGREE WITH HI SPEC

PVT REVISION HISTORY

PVT - 9NOV98
PVT BUG LIST FROM RADAR:
TAG #1 - WRONG F/W LYNX CHIP WAS STUFFED ON SOME BOARDS
TAG #2 - SDRAM FAILURES CAUSED FROM TOO SLOW A RISE TIME
TAG #3 - SDRAM SDBA(1) STILL HAS TOO SLOW A RISE TIME UNDER HEAVY LOADS
TAG #4 - BURGUNDY SOUND CHIP FAILS TO COME READY ON COLD BOOT

NO TAG #1 - R285, R1069 & C807 COULD CRACK AS FPB CONNECTOR IS INSERTED
NO TAG #2 - ETHERNET CAPS SHOULD BE 1.5KV MINIMUM

PRODUCTION REVISION HISTORY

PROD - 12JAN99
PVT BUG LIST FROM RADAR:
TAG #1 - DIMM SIGNAL SD1BA(1) HAS BAD SIGNAL QUALITY

NOTICE OF PROPRIETARY PROPERTY
THE INFORMATION CONTAINED HEREIN IS THE PROPRIETARY
PROPERTY OF APPLE COMPUTER, INC. THE POSSESSOR
AGREES TO THE FOLLOWING
(I) TO MAINTAIN THE DOCUMENT IN CONFIDENCE
(II) NOT TO REPRODUCE OR COPY IT
(III) NOT TO REVEAL OR PUBLISH IT IN WHOLE OR PART

ECS CAD GENERATED
APPLE CONFIDENTIAL

Revision History

SIZE	DRAWING NUMBER	REV.
D	051-0777	C
SCALE	SHT 44	OF 43
NONE		

Apple Computer, Inc

YOSEMITE PRODUCTION REV-C BOM

Yosemite_prodcv.bom									
Date: 99/1/20 - Time: 14:21:51									
Item#	Qty	Part#	Package	Description	Value	Voltage	Wattage	Tolerance	Ref. Designators
STUFF List:									
1	4	101S1000	RES_0805	RESISTOR,	0		1/10W		R80,R243,R513,R667
2	1	101S1101	RES_0805	RESISTOR,	10		1/10W		R455
3	4	101S1105	RES_0805	RESISTOR,	100K		1/10W		R512,R516,R994,R1040
4	2	101S1273	RES_0805	RESISTOR,	2.7K		1/10W		R511,R514
5	3	101S2471	RES_2010	RESISTOR,	47		1/2W	5%	R411,R412,R413
6	1	101S4000	RES_1210	RESISTOR,	0		1/4W		R83
7	1	101S6151	RES_2512	RESISTOR,	15		1W		R1074
8	3	101S6201	RES_2512	RESISTOR,	20		1W		R522,R523,R918
9	1	101S8101	RES_1206	RESISTOR,	10		1/8W		R701
10	1	101S8330	RES_1206	RESISTOR,	3.3		1/8W		R702
11	1	106S1822	RES_0805	RESISTOR,	182		1/10W	1%	R518
12	4	110S1001	RES_0603	RESISTOR,	10		1/16W	1%	R510,R515,R885,R1060
13	2	110S1002	RES_0603	RESISTOR,	100		1/16W	1%	R715,R1052
14	8	110S1004	RES_0603	RESISTOR,	10k		1/16W	1%	R45,R46,R451,R463,R468,R517,R520,R521
15	6	110S1005	RES_0603	RESISTOR,	100k		1/16W	1%	R252,R253,R255,R257,R258,R259
16	2	110S2214	RES_0603	RESISTOR,	22.1K		1/16W	1%	R554,R1043
17	2	110S3011	RES_0603	RESISTOR,	30.1		1/16W	1%	R458,R464
18	10	110S4991	RES_0603	RESISTOR,	49.9		1/16W	1%	R432,R433,R434,R436,R437,R438,R486,R487,R490,R491
19	2	110S7501	RES_0603	RESISTOR,	75		1/16W	1%	R435,R439
20	8	110S8252	RES_0603	RESISTOR,	825		1/16W	1%	R407,R449,R450,R452,R453,R454,R456,R460
21	23	112-8200	RP_8MINI_SMJ	RPAK, 8 PIN, ISOLATED,	10		1/16W		RP11,RP12,RP18,RP29,RP30,RP34,RP35,RP36,RP37,RP44,
									RP45,RP46,RP47,RP50,RP51,RP52,RP53,RP54,RP55,RP56,
									RP144,RP145,RP164
					22		1/16W		RP6,RP8,RP13,RP14,RP15,RP16,RP17,RP19,RP20,RP21,
22	48	112-8204	RP_8MINI_SMJ	RPAK, 8 PIN, ISOLATED,					RP26,RP27,RP28,RP31,RP32,RP38,RP39,RP48,RP49,RP104,
									RP108,RP109,RP110,RP111,RP112,RP113,RP114,RP115,RP123,RP128,
									RP129,RP130,RP131,RP136,RP137,RP138,RP139,RP140,RP141,RP142,
									RP143,RP147,RP148,RP149,RP151,RP167,RP172,RP173
									RP1,RP2,RP105,RP106,RP107,RP116,RP124,RP125,RP126
					33		1/16W		RP62,RP63
23	9	112-8207	RP_8MINI_SMJ	RPAK, 8 PIN, ISOLATED,	100		1/16W		RP9,RP10,RP23,RP24,RP33,RP40,RP61,RP117,RP118,RP119,
24	2	112-8216	RP_8MINI_SMJ	RPAK, 8 PIN, ISOLATED,	4.7K		1/16W		RP120,RP121,RP122,RP127,RP132,RP134,RP135,RP146,RP150,RP152,
25	29	112-8241	RP_8MINI_SMJ	RPAK, 8 PIN, ISOLATED,					RP153,RP155,RP156,RP161,RP162,RP163,RP168,RP169,RP170
									RP25,RP41,RP42,RP43,RP57,RP154,RP157,RP158,RP159,RP160,
					10K		1/16W		RP174,RP175,RP176
26	13	112-8248	RP_8MINI_SMJ	RPAK, 8 PIN, ISOLATED,					RP5,RP7,RP100,RP103
					100K		1/16W		R26,R90,R120,R125,R136,R139,R192,R193,R208,R209,
27	4	112-8264	RP_8MINI_SMJ	RPAK, 8 PIN, ISOLATED,	0		1/16W		R218,R219,R220,R222,R228,R237,R260,R267,R268,R269,
28	47	113S1000	RES_0603	RESISTOR,					R288,R289,R290,R560,R561,R567,R613,R614,R663,R677,
									R692,R704,R712,R714,R755,R765,R803,R879,R883,R912,
									R922,R927,R949,R957,R960,R981,R1036
					10		1/16W		R85,R86,R87,R170,R195,R225,R241,R245,R250,R251,
									R285,R345,R547,R548,R549
29	15	113S1101	RES_0603	RESISTOR,					R254,R993
					100		1/16W		R4,R25,R29,R126,R144,R145,R165,R177,R181,R185,
30	2	113S1102	RES_0603	RESISTOR,	1K		1/16W		R190,R266,R281,R422,R471,R476,R539,R562,R563,R565,
31	38	113S1103	RES_0603	RESISTOR,					R640,R687,R754,R756,R757,R790,R809,R832,R900,R921,
									R946,R950,R951,R952,R958,R959,R986,R1030
					10K		1/16W		R2,R10,R66,R84,R194,R205,R210,R238,R273,R274,
32	71	113S1104	RES_0603	RESISTOR,					

YOSEMITE PRODUCTION REV-C BOM

								R275,R282,R318,R414,R415,R416,R418,R524,R528,R529, R531,R532,R534,R535,R536,R538,R664,R688,R710,R761, R825,R899,R903,R904,R905,R906,R907,R935,R936,R937, R940,R941,R955,R968,R970,R972,R973,R974,R975,R978, R980,R985,R999,R1000,R1001,R1002,R1004,R1008,R1011,R1012, R1013,R1016,R1017,R1022,R1023,R1031,R1034,R1047,R1049,R1061, R1069
33	5	113S1105	RES_0603	RESISTOR,	100K		1/16W	R5,R233,R234,R235,R783
34	18	113S1151	RES_0603	RESISTOR,	15		1/16W	R152,R153,R154,R155,R156,R157,R158,R159,R162,R163, R171,R172,R847,R848,R849,R850,R854,R887
35	1	113S1153	RES_0603	RESISTOR,	1.5K		1/16W	R261
36	10	113S1154	RES_0603	RESISTOR,	15K		1/16W	R227,R236,R601,R639,R657,R658,R659,R660,R995,R996
37	1	113S1155	RES_0603	RESISTOR,	150K		1/16W	5% R637
38	2	113S1182	RES_0603	RESISTOR,	180		1/16W	R196,R198
39	1	113S1205	RES_0603	RESISTOR,	200K		1/16W	R216
40	157	113S1221	RES_0603	RESISTOR,	22		1/16W	R6,R7,R8,R19,R20,R28,R33,R34,R37,R40, R47,R48,R49,R50,R51,R52,R53,R54,R55,R56, R57,R58,R59,R60,R61,R67,R69,R88,R91,R92, R95,R96,R97,R98,R99,R101,R102,R103,R104,R105, R106,R107,R108,R113,R117,R118,R119,R127,R128,R138, R150,R160,R272,R283,R293,R320,R419,R421,R423,R425, R472,R477,R485,R525,R527,R530,R533,R543,R544,R545, R546,R551,R552,R569,R574,R591,R596,R597,R605,R608, R641,R671,R672,R673,R675,R676,R678,R679,R680,R681, R682,R683,R684,R685,R689,R690,R691,R709,R711,R729, R735,R738,R739,R743,R744,R746,R762,R781,R782,R784, R786,R787,R789,R791,R793,R796,R797,R798,R799,R800, R804,R822,R823,R824,R826,R827,R828,R829,R839,R840, R853,R855,R856,R857,R858,R859,R860,R861,R864,R865, R867,R877,R878,R880,R884,R909,R910,R913,R954,R971, R976,R997,R998,R1009,R1032,R1072,R1073
41	1	113S1222	RES_0603	RESISTOR,	220		1/16W	R1026
42	4	113S1223	RES_0603	RESISTOR,	2.2K		1/16W	R16,R17,R24,R888
43	4	113S1271	RES_0603	RESISTOR,	27		1/16W	R78,R79,R630,R656
44	47	113S1331	RES_0603	RESISTOR,	33		1/16W	R1,R31,R32,R110,R111,R112,R121,R122,R123,R124, R141,R142,R143,R146,R147,R148,R149,R164,R173,R174, R175,R176,R178,R179,R180,R182,R183,R184,R186,R187, R188,R189,R270,R271,R607,R740,R741,R742,R749,R750, R752,R794,R802,R805,R807,R902,R929
45	12	113S1332	RES_0603	RESISTOR,	330		1/16W	R276,R400,R402,R426,R428,R509,R580,R581,R606,R806, R808,R987
46	1	113S1333	RES_0603	RESISTOR,	3.3K		1/16W	R1059
47	2	113S1335	RES_0603	RESISTOR,	330K		1/16W	R134,R224
48	1	113S1392	RES_0603	RESISTOR,	390		1/16W	R484
49	32	113S1471	RES_0603	RESISTOR,	47		1/16W	R14,R21,R166,R408,R409,R459,R488,R519,R556,R559, R570,R571,R572,R573,R575,R576,R615,R624,R628,R629, R650,R655,R670,R730,R731,R732,R785,R788,R869,R938, R1018,R1019
50	3	113S1472	RES_0603	RESISTOR,	470		1/16W	R242,R934,R1033
51	112	113S1473	RES_0603	RESISTOR,	4.7K		1/16W	R11,R12,R35,R36,R38,R39,R41,R42,R62,R63, R64,R65,R70,R89,R93,R94,R100,R114,R115,R116, R129,R130,R131,R132,R133,R135,R167,R168,R169,R199, R206,R213,R215,R246,R247,R248,R249,R256,R286,R287, R424,R427,R429,R430,R431,R474,R475,R478,R481,R482, R526,R537,R541,R553,R555,R564,R566,R568,R604,R645,

YOSEMITE PRODUCTION REV-C BOM

								R647,R651,R666,R674,R695,R696,R697,R698,R699,R700, R707,R717,R720,R721,R722,R723,R724,R725,R726,R727, R728,R733,R734,R736,R737,R745,R767,R768,R769,R770, R771,R772,R773,R774,R775,R776,R777,R778,R779,R780, R792,R795,R811,R820,R868,R886,R979,R982,R1006,R1007, R1020,R1039
52	14	113S1474	RES_0603	RESISTOR,	47K		1/16W	R13,R15,R22,R457,R461,R593,R594,R598,R599,R600, R602,R603,R638,R1044
53	1	113S1475	RES_0603	RESISTOR,	470K		1/16W	R983
54	1	113S1516	RES_0603	RESISTOR,	5.1M		1/16W	5% R223
55	3	113S1563	RES_0603	RESISTOR,	5.6K		1/16W	R30,R462,R467
56	6	113S1821	RES_0603	RESISTOR,	82		1/16W	R18,R27,R109,R540,R708,R747
57	1	113S1823	RES_0603	RESISTOR,	8.2K		1/16W	R636
58	1	127S1001	CAP_TANTA_SM	CAPACITOR, POLARIZED,	1UF	10V	20%	C245
59	17	127S1008	CAP_TANTR_SMA	CAPACITOR, POLARIZED,	1UF	10V	10%	C20,C21,C22,C23,C26,C27,C28,C32,C34,C36, C37,C38,C98,C411,C413,C420,C428
60	25	127S1015	CAP_TANTA_SM	CAPACITOR, POLARIZED,	10UF	6.3V	20%	C1,C3,C13,C104,C136,C142,C147,C150,C162,C186, C188,C190,C242,C243,C247,C252,C267,C272,C282,C301, C319,C528,C560,C817,C818
61	6	127S1021	CAP_TANTD_SM	CAPACITOR, POLARIZED,	100UF	10V	20%	C100,C101,C229,C318,C821,C837
62	3	127S2204	CAP_TANTR_SMA	CAPACITOR, POLARIZED,	2.2UF	6.3V	10%	C95,C96,C97
63	2	127S2210	CAP_TANTD_SM	CAPACITOR, POLARIZED,10UF	22UF	16V	20%	C132,C339
64	3	127S2218	CAP_TANTA_SM	CAPACITOR, TANTALUM	22UF	6.3V	10%	C43,C424,C433
65	2	127S3305	CAP_TANTA_SM	CAPACITOR, TANTALUM	3.3UF	16V	10%	C294,C346
66	3	127S3306	CAP_TANTB_SM	CAPACITOR, TANTALUM	3.3UF	25V	20%	C12,C292,C481
67	2	127S3310	CAP_TANTD_SM	CAPACITOR, POLARIZED,	33UF	20V	20%	C258,C291
68	27	127S4714	CAP_TANTD_SM	CAPACITOR, POLARIZED,	47UF	16V	20%	C4,C6,C10,C15,C19,C31,C39,C119,C122,C131, C161,C163,C178,C200,C203,C208,C220,C233,C259,C260, C269,C290,C293,C295,C296,C400,C527
69	2	128S0202	CAP_TANTE_SM	CAP,TANT,0.10ESR@100KHZ	330UF	6V	20%	C331,C337
70	8	128S0204	CAP_TANTD_SM	CAPACITOR, POLARIZED,	100UF	10V	20%	C268,C317,C332,C333,C334,C833,C834,C836
71	1	131S1013	CAP_0603	CAPACITOR, NON-POLARIZED,	10PF	50V	5%	C819
72	17	131S1025	CAP_0603	CAPACITOR, NON-POLARIZED,	100PF	50V	5%	C55,C56,C57,C58,C195,C196,C197,C198,C341,C599, C637,C638,C745,C746,C831,C1701,C1702
73	12	131S1034	CAP_0603	CAPACITOR, NON-POLARIZED,	1000PF	25V	5%	C33,C35,C404,C405,C410,C412,C421,C422,C425,C429, C431,C432
74	10	131S1512	CAP_0603	CAPACITOR, NON-POLARIZED,	15PF	50V	5%	C16,C59,C60,C61,C62,C63,C610,C617,C618,C653
75	5	131S3314	CAP_0603	CAPACITOR, NON-POLARIZED,	33PF	50V	10%	C505,C507,C530,C531,C820
76	1	131S4712	CAP_0603	CAPACITOR, NON-POLARIZED,	47PF	50V	10%	C523
77	1	131S4723	CAP_0603	CAPACITOR, NON-POLARIZED,	470PF	50V	10%	C82
78	4	131S5111	CAP_0805	CAPACITOR, NON-POLARIZED,	51PF	50V	5%	C66,C67,C68,C69
79	1	131S5621	CAP_0603	CAPACITOR, NON-POLARIZED,	560PF	50V	5%	C830
80	470	132S1046	CAP_0603	CAPACITOR, NON-POLARIZED,	0.01UF	50V	20%	C2,C5,C7,C8,C9,C11,C14,C18,C25,C30, C40,C46,C54,C64,C65,C70,C71,C80,C81,C83, C84,C85,C86,C87,C88,C89,C90,C91,C92,C93, C94,C99,C106,C107,C108,C109,C110,C111,C112,C113, C114,C115,C116,C117,C118,C120,C121,C123,C124,C125, C126,C127,C128,C129,C135,C137,C144,C145,C146,C149, C151,C152,C153,C154,C155,C157,C158,C159,C160,C164, C165,C166,C167,C168,C169,C170,C171,C172,C173,C174, C175,C176,C177,C179,C180,C181,C182,C183,C184,C187, C189,C193,C194,C199,C201,C202,C204,C205,C206,C207, C209,C210,C211,C212,C213,C214,C215,C216,C217,C218, C219,C221,C222,C224,C227,C228,C230,C231,C232,C234, C235,C236,C237,C238,C239,C240,C241,C244,C246,C248,

YOSEMITE PRODUCTION REV-C BOM

									C250,C253,C254,C255,C256,C257,C261,C262,C263,C264, C265,C266,C273,C274,C276,C277,C278,C279,C280,C283, C284,C285,C286,C287,C288,C289,C297,C298,C299,C300, C302,C303,C306,C307,C308,C309,C314,C315,C320,C321, C322,C323,C325,C330,C338,C340,C342,C344,C348,C350, C351,C352,C353,C401,C402,C440,C441,C442,C443,C444, C445,C446,C447,C448,C449,C450,C451,C452,C453,C454, C455,C456,C457,C458,C459,C460,C467,C470,C473,C480, C482,C483,C484,C485,C486,C487,C489,C490,C492,C493, C494,C495,C496,C497,C498,C499,C503,C509,C510,C511, C512,C513,C514,C515,C516,C517,C518,C519,C520,C521, C522,C524,C525,C526,C541,C543,C544,C545,C546,C547, C548,C549,C550,C551,C552,C553,C554,C555,C556,C557, C558,C559,C561,C562,C563,C564,C565,C566,C567,C568, C570,C571,C572,C573,C575,C576,C577,C578,C579,C580, C582,C583,C584,C585,C586,C587,C588,C589,C590,C591, C592,C593,C594,C595,C596,C597,C600,C601,C602,C603, C604,C605,C606,C607,C608,C612,C613,C614,C615,C616, C619,C620,C621,C622,C623,C624,C625,C626,C627,C628, C629,C631,C632,C633,C634,C635,C636,C639,C640,C641, C642,C643,C644,C645,C646,C648,C650,C651,C654,C655, C656,C657,C658,C659,C660,C662,C663,C664,C665,C666, C667,C668,C669,C670,C671,C672,C674,C675,C676,C677, C678,C679,C680,C681,C682,C683,C684,C685,C686,C689, C690,C691,C692,C693,C694,C695,C696,C697,C700,C701, C702,C703,C704,C705,C706,C707,C708,C709,C710,C711, C712,C713,C714,C715,C717,C718,C719,C720,C721,C722, C723,C724,C726,C727,C728,C729,C730,C732,C733,C734, C735,C738,C739,C740,C741,C742,C743,C744,C747,C748, C749,C750,C751,C752,C753,C755,C756,C757,C758,C759, C762,C763,C764,C765,C766,C767,C768,C769,C771,C773, C778,C779,C780,C781,C782,C783,C784,C785,C786,C788, C789,C790,C791,C792,C793,C795,C796,C798,C799,C800, C801,C852,C1043,C1044,C1045,C1046,C1047,C1048,C1049,C1700
81	1	132S1053	CAP_0805	CAPACITOR, NON-POLARIZED,	0.1UF	25V	20%	C828	
82	23	132S1056	CAP_0603	CAPACITOR, NON-POLARIZED,	0.1UF	16V	-20,+80%	C17,C29,C42,C45,C349,C414,C415,C416,C417,C418, C419,C423,C426,C427,C435,C436,C437,C504,C829,C832, C835,C845,C853	
								C430,C434	
83	2	132S1063		CAP, CER, 1UF, 10V, 10%				C130,C542	
84	2	132S4743	CAP_0603	CAPACITOR, NON-POLARIZED,	0.047UF	16V	5%	C324,C802,C803,C804	
85	4	138S0303	CAP_1206	CAPACITOR, NON-POLARIZED,	3.3UF	16V	-20,+80%	C335,C478,C479	
86	3	138S0312	CAP_0805	CAPACITOR, NON-POLARIZED,	1.0UF	16V	-20,+80%	C41,C44,C105,C133,C134,C148,C156,C225,C226,C249, C251,C275,C281,C343,C345,C347,C438,C439,C474,C488, C491,C532,C569,C574,C581,C630,C647,C649,C661,C673, C687,C716,C725,C731,C736,C737,C760,C770,C772,C787, C794	
87	41	138S0313	CAP_0805	CAPACITOR, NON-POLARIZED,	2.2UF	16V	-20,+80%	L98	
								L70,L71,L72,L73	
								L1,L2,L4,L80,L81,L82,L83	
								L16,L21,L22,L23,L24,L25,L26,L27,L28,L29, L30,L32,L34,L50,L53,L92,L97	
								L11,L12,L68,L69	
88	1	152S0080	IND_2W423_SM	INDUCTOR,	3.3UH			L6,L7,L8,L9,L10,L13,L14,L19,L20,L51, L52,L74,L75,L76,L77,L78,L79,L84,L85,L86,	
89	4	155S0051	IND_0603	INDUCTOR,	300HM				
90	7	155S0052	IND_0603	INDUCTOR,	1000OHM				
91	17	155S0070	FERRITE	INDUCTOR,	FERRITE-500MA				
92	4	155S0086	IND_1812_SM	INDUCTOR,	FERRITE-1.5A				
93	28	155S0093	IND_0603	INDUCTOR,	FER-EMI-100-OHM				

YOSEMITE PRODUCTION REV-C BOM

									L87,L88,L89,L90,L91,L101,L109,L110
94	1	156-0034	IND_R180_D680	INDUCTOR,	2.8UH				L33
95	1	157S0171	XFR_16W455_SM	XFR, HIGH SPEED LAN MAGNETICS MODULES					T1
96	1	197S0100	CRY_2PIN_SM	CRYSTAL,	14.318M				Y3
97	1	197S0153	CRY_2PIN_SM	CRYSTAL,	25.0000M				Y2
98	1	197S0211	CRY_4PIN_SM	CRYSTAL, 4 PIN,	32.768K				Y4
99	1	197S0907	OSC_10X5MM_SM	OSCILLATOR, TRI-STATE,	18.4320M				G3
100	1	310S0008	SSOI_14W211	IC, QUAD 2-INPUT AND GATE, 14 P, TSSOP					U34
101	1	310S0014	SSOI_14W250	IC, LOW VOLTAGE HEX SCHMIDT TRIGGER INVERTER					U47
102	4	310S0015	TSSOP_56W276	IC, 3.3V 18-BIT UNIV BUS XCVR W/RES TRI-STATE OUTS					U42,U43,U44,U45
103	2	310S0245	SSOI-20W253	IC, 74LVCH245A, OCTAL BUS XCVR, TRISTATE					U5,U6
104	1	311S0125	SSOI_14W211	IC, 3.3V QUAD BUS BUFFERS W/3-STATE					U31
105	1	311S0257	SSOI_16W250	IC, 3.3V (5V)QUAD. 2-1 LINE DATA SEL/MULT. TSSOP					U33
106	1	333S0066	SOI_28W407	IC,SRAM,CMOS,32KX8,70NS					U19
107	1	337S0003		IC, ASIC-176-PQFP, LYNX-1					U10
108	1	337S0269		CMD UATA 0646U2-402					U1
109	1	337S0629	BGA_23X23_304	IC, ASIC, PCI TO PCI BRIDGE, 304-P BGA					U22
110	1	337S0630	FLA_16X16_L	IC, ST10040 ETHERNET TRANSCEIVER FOR 10BASE-T					U9
111	1	341S0184		IC, ROM, IEEE DUAL ADR					U16
112	1	341S0262	SOI_28W	IC, MICROCNTRLR, 68HC05E5, UCTLR, 2MHZ, LV, 28P					U40
113	1	341S0520		YOSEMITE FW ROM, PRGMD					U41
114	1	341S0537		1MX8, YOSEMITE FLASH ROM					U37
115	1	343S0120	SOI_8N	IC, LS1176, POWER MONITOR					U46
116	1	343S0177	FLA_20X30_W627	IC,ASIC,AUDIO CODEC,BURGUNDY,100P QFP					U2
117	1	343S1218	CBGA_19X16_303	IC, GRACKLE 4.0, 100MHZ, 303-P BGA					U23
118	1	343S1219	PLC_28	IC, ASIC, GATED CLOCK IIA, 28-P PLCC					U12
119	1	343S1225		PADDTON, BGA, ENET FAST					U18
120	2	353S0208	SOI_8N	IC, POWER DISTRIBUTION SWITCH					U14,U15
121	1	353S0209	SOI_16N	IC, CS5157, 5-BIT BUCK CNVTR PWM, 16P SOIC					U38
122	2	353S0223	SOI_8N	IC, OPAMP TS922ID,DUAL					U8,U32
123	1	353S0393	SOI_8N	IC, LM393, DUAL COMPARATOR					U11
124	2	353S7805	VREG_TO_252	VREG, 78M05, 5V,VOLTAGE REGULATOR, 5V					VR1,VR3
125	1	353S7905	VREG_TO_252	VREG, 79M05 VOLTAGE REGULATOR, -5V					VR2
126	1	355S0016	SOI_8N	AUDIO, LM4861 AUDIO POWER AMP, .5W					U39
127	1	355S0047	SOI_8N	IC, STEREO D/A CONVERTER, DIGITAL AUDIO					U7
128	1	359S0011	SOI_16N	IC, PLL CLOCK GENERATOR, CY2292					U17
129	2	359S0030	SSOI_24W210	IC, 3_3V PHASE-LOCK LOOP CLOCK DRIVER					U20,U35
130	1	359S0034	FLA_52W497	IC, SC683 SYSTEM CLOCK					U25
131	1	359S0038	SSOI_28W280	IC, SG500D 28-P SPREAD SPECTRUM CLK GEN					U24
132	4	371-5354	DIO_SMB_SM	DIODE, SCHOTTKY,	MBRS130T3				D1,D2,D3,D10
133	2	371S0914	DIO_SOT23_E	DIODE,	1N914				D8,D9
134	5	372S0012	TRA_SOT23	TRAN, TP0202T P-CHANNEL, MOSFET	TP0202T				Q4,Q5,Q6,Q7,Q8
135	5	372S3904	TRA_SOT23	TRAN, 2N3904, SM NPN	2N3904				Q10,Q11,Q12,Q56,Q59
136	2	372S3906	TRA_SOT23	TRAN, 2N3906, PNP SM	2N3906				Q9,Q53
137	2	372S7002	TRA_SOT23	TRAN, 2N7002, NFET SM	2N7002				Q21,Q52
138	2	376S0257	SOI_8N	TRA, N-CHANNEL ENHANCEMENT MODE MOSFET	SI4416DY				Q60,Q61
139	1	377S0010	SOI_8W230_65MM	IC, TRANSIENT SUPPRESSOR,8 PIN					U3
140	7	378S0038	LED_1206	LED,	GREEN				DS1,DS4,DS5,DS6,DS7,DS8,DS9
141	1	511-0024	SOC_PGA_288TH	IC, CPU, INTERPOSER					J24
142	3	513-0326	CON_64_5V_ST	CONN, PCI, TH, 64 BIT, 5V, 188-PIN					J9,J10,J11
143	1	513-1325	CON_32_3V_ST	CONN, PCI, TH, 32 BIT, 3V, 120 PIN					J12
144	1	515-1080	CON_M2RT_HDRF	CONN, HDR, RT, POLARIZED, REFLO					J34
145	1	515-1081	CON_M4RT_HDRE	CONN, HDR, RT, 0.1 CNTRS, POLARIZED REFLO					J8
146	1	515-1443	CON_M20RT_HDR	CONN, INT. FLPPY, .100 X .100					J31
147	1	515-1466	CON_M3RT_LOCK	CONN, RT ANGLE, FRICTION LOCK HDR					J2

YOSEMITE PRODUCTION REV-C BOM

148	1	515-1563	CON_M3ST_LCK	CONN, HDR, STR, 0.1" CTR, FRIC LCK, REFLOW				J5
149	1	515-1582	CON_M20ST_PWRA	CONN,PWR,20 PIN,MINI FIT				J23
150	2	515-1588	CON_M40ST_HDR	CONN,HDR,STR,2-ROW,0.1 PTCH,40P,W/O PIN 20,REF				J1,J15
151	1	515-1703	CON_M22ST_2MM	CONN, HDR, STR, 2 ROW, HI TEMP WITH STANDOFFS				J25
152	1	517-0249		CONN, USB, FOXCONN 2, 2P				J4
153	4	517-0782	CON_168ST_UDRM	CONN, SKT, DIMM, VERT, 3.3V, 168P				J19,J20,J21,J22
154	1	517-1259	CON_4RT_DIN_SR	CONN, SHIELDED, LOCKING MINI DIN, BRDLOCKS REFLOW				J7
155	1	519-0389		CONN, RJ45 SHORT, SHIELD				J6
156	1	519-0653	CON_STEREO3_4	CONN, PHONO JACK 4 W/3 POS				J3
157	1	519S0032	CON_F70SM_BTBTB	CONN, RCPT, BTB, 0.635MM				J14
158	1	519S0045	CON_F40SM_BTBTB	CONN, 40-P, .8MM, RCPT.				J13
159	1	525-0057		LITH, BAT HOLDER, 1P				BT1
160	2	705S0201	SWI_283X255_SM	SWITCH, 1 SWITCH, 4 PINS				S4,S5
161	1	740S0500	FUSE_POLY_SMD	FUSE, POLY, 0.9A	0.9AMP			F1
162	1	742-0029		BATTERY, LITHIUM, 3.6V				BT1
163	1	820-1049-A		PCB, YOSEMITE MLB				PCB1
164	1	875-1030		EMI SUPRESSOR, 100M-3GHZ				U25
BOM Option =ADR BUF, IDT-ALVCH (ALT)								
230	4	310S2244		IC, IDT-ALVCH16244, 2.6nS				U26,U27,U29,U30
BOM Option =ADR BUF, PHL-ALVCH (STD)								
231	4	310S6244		IC, PHL-ALVCH16244, 2.6nS				U26,U27,U29,U30
BOM Option =CTL BUF, IDT-ALVCH (ALT)								
232	1	310S2244		IC, IDT-ALVCH16244, 2.6nS				U28
BOM Option =CTL BUF, PHL-ALVCH (STD)								
233	1	310S6244		IC, PHL-ALVCH16244, 2.6nS				U28
BOM Option =USB IC, LUCENT								
234	1	101S1000	RES_0805	RESISTOR,	0		1/10W	R652
235	2	113S1000		RES, FF, 0 OHM, 5%, 1/16W				R231,R232
236	1	155S0070	FERRITE	INDUCTOR,	FERRITE-500MA			L18
237	1	337S0201		LUCENT 302 USB 100P PQFP				U13
BOM Option =USB IC, OPTI								
238	1	101S1000		RES, FF, 0 OHM, 5%, 0.1W				R586
239	2	113S1104	RES_0603	RESISTOR,	10K		1/16W	R229,R230
240	1	155S0070		FERRITE - 500MA				L17
241	1	337S0551		OPTI 82C861 USB 100P PQFP				U13
NO STUFF List:								
1	1	009-		PRGM, YOSEMITE 1MX8				U37
2	1	009-5911		PROG, FW, YOSEMITE				U41
3	1	009-5934		PROG, CMD HACK, YOSEMITE				U48
4	1	009-5939		PRGM, YOSEMITE 1MX8				U37
5	3	101S1000	RES_0805	RESISTOR,	0		1/10W	R244,R586,R665
6	1	101S1221	RES_0805	RESISTOR,	22		1/10W	R217
7	10	101S1241	RES_0805	RESISTOR,	24		1/10W	R764,R766,R833,R834,R845,R846,R851,R852,R932,R933
8	1	110S2003		RES, FF, 2K OHM, 1%, 1/16W				R1053
9	1	110S2213	RES_0603	RESISTOR,	2.21K		1/16W	R221
10	1	110S4173		RES, FF, 4.17K OHM, 1%, 1/16W				R1053
11	1	110S4993		RES, FF, 4990 OHM, 1%, 1/16W				R219
12	1	110S8453		RES, FF, 8.45K OHM, 1%, 1/16W				R1053

YOSEMITE PRODUCTION REV-C BOM



13	1	112-8204	RP_8MINI_SMJ	RPAK, 8 PIN, ISOLATED,	22		1/16W		RP22
14	4	112-8241	RP_8MINI_SMJ	RPAK, 8 PIN, ISOLATED,	4.7K		1/16W		RP3,RP4,RP101,RP102
15	3	112-8248	RP_8MINI_SMJ	RPAK, 8 PIN, ISOLATED,	10K		1/16W		RP165,RP166,RP171
16	80	113S1000	RES_0603	RESISTOR,	0		1/16W		R44,R140,R214,R218,R219,R220,R231,R232,R277,R278, R279,R280,R284,R592,R595,R646,R668,R686,R703,R705, R706,R713,R751,R753,R758,R759,R760,R814,R815,R816, R817,R835,R836,R837,R838,R842,R871,R872,R873,R874, R875,R876,R881,R882,R889,R890,R891,R892,R893,R894, R895,R896,R897,R911,R914,R915,R920,R923,R924,R925, R926,R928,R930,R946,R948,R953,R961,R962,R963,R969, R992,R1005,R1037,R1048,R1054,R1055,R1056,R1057,R1058,R1064
17	29	113S1103	RES_0603	RESISTOR,	1K		1/16W		R75,R76,R81,R82,R151,R191,R203,R204,R211,R212, R263,R264,R265,R420,R748,R810,R821,R831,R841,R843, R844,R862,R863,R919,R931,R946,R958,R959,R1063
18	13	113S1104	RES_0603	RESISTOR,	10k		1/16W		R3,R197,R201,R470,R939,R956,R984,R1003,R1015,R1024, R1025,R1050,R1051
19	5	113S1105	RES_0603	RESISTOR,	100K		1/16W		R73,R74,R410,R635,R947
20	1	113S1112	RES_0603	RESISTOR,	110		1/16W		R9
21	6	113S1154	RES_0603	RESISTOR,	15K		1/16W		R916,R917,R1041,R1042,R1045,R1046
22	1	113S1205	RES_0603	RESISTOR,	200K		1/16W		R1075
23	11	113S1221	RES_0603	RESISTOR,	22		1/16W		R68,R71,R72,R77,R137,R161,R202,R669,R818,R819, R901
24	1	113S1223	RES_0603	RESISTOR,	2.2K		1/16W		R23
25	1	113S1273	RES_0603	RESISTOR,	2.7K		1/16W		R1062
26	1	113S1274		RES, FF, 27K OHM, 5%, 1/16W					R207
27	5	113S1332	RES_0603	RESISTOR,	330		1/16W		R262,R291,R489,R616,R870
28	1	113S1335	RES_0603	RESISTOR,	330K		1/16W	5%	R557
29	16	113S1471	RES_0603	RESISTOR,	47		1/16W		R43,R239,R240,R479,R480,R483,R542,R763,R801,R830, R964,R965,R966,R967,R1014,R1021
30	3	113S1472	RES_0603	RESISTOR,	470		1/16W		R200,R321,R663
31	8	113S1473	RES_0603	RESISTOR,	4.7K		1/16W		R226,R401,R649,R661,R866,R1010,R1035,R1038
32	1	113S1822	RES_0603	RESISTOR,	820		1/16W		R662
33	2	127S1008		CAP, TANT, 1UF, 10V, 10%					C430,C434
34	2	127S3305	CAP_TANTA_SM	CAPACITOR, POLARIZED,	3.3UF	16V		10%	C24,C311
35	1	127S4714		CAP, CER 3.3UF, 20%, 16V					C329
36	10	131S1025	CAP_0603	CAPACITOR, NON-POLARIZED,	100PF	50V		5%	C822,C823,C824,C825,C838,C839,C840,C841,C842,C843
37	5	131S1512	CAP_0603	CAPACITOR, NON-POLARIZED,	15PF	50V		5%	C403,C475,C476,C826,C827
38	1	131S1822	CAP_0603	CAPACITOR, NON-POLARIZED,	180PF	50V		5%	C506
39	2	131S3322	CAP_0603	CAPACITOR, NON-POLARIZED,	330PF	50V		10%	C609,C611
40	10	131S4712	CAP_0603	CAPACITOR, NON-POLARIZED,	47PF	50V		10%	C468,C469,C471,C472,C652,C688,C698,C699,C754,C814
41	6	131S4723	CAP_0603	CAPACITOR, NON-POLARIZED,	470PF	50V		10%	C806,C807,C808,C810,C811,C812
42	2	132S1032	CAP_0603	CAPACITOR, NON-POLARIZED,	0.001UF	50V		20%	C537,C540
43	11	132S1046	CAP_0603	CAPACITOR, NON-POLARIZED,	0.01UF	50V		20%	C47,C270,C271,C304,C305,C325,C539,C714,C715,C761, C809
44	1	132S1056	CAP_0603	CAPACITOR, NON-POLARIZED,	0.1UF	16V		-20,+80%	C336
45	1	138S0303		CAP, CER 3.3UF, 20%, 16V					C324
46	1	138S0312	CAP_0805	CAPACITOR, NON-POLARIZED,	1.0UF	16V		-20,+80%	C805
47	4	155S0070	FERRITE	INDUCTOR,	FERRITE-500MA				L15,L17,L31,L35
48	4	155S0093	IND_0603	INDUCTOR,	FER-EMI-100-OHM				L93,L94,L95,L96
49	1	197S0525	OSC_4PIN_SM	OSCILLATOR, TRI-STATE,	48.000M				G1
50	1	197S0906	OSC_10X5MM_SM	OSCILLATOR, TRI-STATE,	18.4320M				G2
51	1	293S0125	SOL_14N	IC, QUAD BUFFER W/TRI-STATE OUT					U4
52	1	312S3244	SSOL_20W250	IC, 3.3-V ABT OCTAL BUFFER/DRIVER W/3-STATE					U21
53	1	335S0253		IC, ROM, CMOS, 128X8, 64X16					U16
54	1	335S0266		PLD, GAL16V8, 10NS, PLCC					U48

YOSEMITE PRODUCTION REV-C BOM

55	1	335S0341		EEPROM, 256X8, BLANK					U41
56	1	335S0350		FLASH, 1MB, BTM BT, 110NS					U37
57	1	335S0354		FLASH, 1/2MB, BTM BT, 110NS					U37
58	1	337-2323		CPU, 350MHZ, 1MB, MOTO					J24
59	1	337-2324		CPU, 300MHZ, 512K, MOTO					J24
60	1	337-2325		CPU, 400MHZ, 1MB, MOTO					J24
61	1	337-2421		CPU, 300MHZ, 512K, IBM					J24
62	1	337-2424		CPU, 350MHZ, 1MB, IBM					J24
63	1	337-2426		CPU, 400MHZ, 1MB, IBM					J24
64	1	337-2520		CPU, 300MHZ, 512K, MOTO DYL					J24
65	1	337-2521		CPU, 350MHZ, 1MB, MOTO, DYL					J24
66	1	337-2522		CPU, 400MHZ, 1MB, MOTO, DYL					J24
67	1	337S0257		CMD UATA 0646U2-400					U1
68	1	337S0260		IC, ASIC-176-PQFP, LYNX-2					U10
69	1	337S7095		CMD 0670A USB 100P PQFP					U13
70	1	341S0450		IC, ROM, IEEE SINGLE ADR					U16
71	1	341S0534		CMD HACK PLD, PRGMD					U48
72	1	341S0537		1MX8, YOSEMITE FLASH ROM					U37
73	1	343S1211		PADDTON, BGA, ENET STD					U18
74	4	371S0914	DIO_SOT23_E	DIODE,	1N914				D4,D5,D6,D7
75	3	372S3904	TRA_SOT23	TRAN, 2N3904, SM NPN	2N3904				Q1,Q19,Q55
76	2	372S3906	TRA_SOT23	TRAN, 2N3906, PNP SM	2N3906				Q20,Q54
77	1	511S0019		SCKT, TSOP, 0.5MM, 40P					U37
78	2	515-0053	CON_2ST_HDRA	CONN, 2 PIN STRAIGHT HEADER					J26,J27
79	1	515-0930	CON_M16ST_HDR	CONN, 16 PIN STRAIGHT HEADER					J28
80	1	515-1081	CON_M4RT_HDRE	CONN, HDR, RT, 0.1 CNTRS, POLARIZED REFLO					J35
81	1	515-1083		CON, 3P RT-ANGLE					J33
82	1	515-1464	CON_M4ST_HDRD	CONN, HDR, ST, 1-ROW, 0.1 PITCH, 4 POS 3-PINS					J30
83	1	517-0260		CONN, USB, OTHER, 2P					J4
84	1	517-0977	CON_5JKSMA_200	CONN,COAX JACK,STR,SMA,PCB MT					J18
85	1	517-0995		CONN, USB, FOXCONN 1, 2P					J4
86	2	517-1230		CONN, SHUNT JUMPER					J26,J27
87	1	519-0857		CONN, RJ45, SHIELD, 2 LEDS					J6
88	1	519-1100		JMPR, BLACK, 300/100/66/33					J25
89	1	519-1101		JMPR, BLUE, 350/100/66/33					J25
90	1	519-1102		JMPR, WHITE, 400/100/66/33					J25
91	1	519-1103		JMPR, YELLOW, 450/100/66/33					J25
92	1	519-1104		JMPR, RED, 500/100/66/33					J25
93	1	520-0344		LITH, BAT HOLDER, TOP					BT1
94	1	525-0055		LITH, BAT HOLDER, BOTTOM					BT1
95	1	609-0066		SPKR ASSY, YOSEMITE					J34
96	1	630-		FDB, FUJI PHY					U13
97	1	630-2732		FDB, TI PHY					U13
98	1	731-0062		SPKR, 8-OHM, 2W, 40x70MM					J34
99	1	740S0505		FUSE, 2.5A 15V					F7
100	2	740S0507	FUSE_POLY_350	FUSE,	1.5AMP				F2,F4
101	1	742-0029		BATTERY, LITHIUM, 3.6V					BT1
102	1	PN-PROM-1MX16-120-TSOP	TSOP_44W445	IC, 1Mx16, 120NS MASK PROM					U36
NOTE: FOLLOWING AREA PROVIDED FOR REFERENCE ONLY									
The Bom Options used to generate this list were:									
ARB PWR, +3.3V									
BATT, LITHIUM 1P									
CLK EMI SUP, ENA									
CPU CAPS, ENA									

YOSEMITE PRODUCTION RED-C BOM

CPU CLKS, NORM		
CPU CORE, DIG STD		
CPU I/O CAPS, ENA		
CUDA PWR, SFT		
DVD CAP, CER		
DVD INPUT, DIG		
DVD VIA, PCI		
ENET LED, DIS		
FLASH PRGM, 5V		
FLASH PWR, 3.3V		
FPB LED CNTL, ENA		
FW IC, TI-1		
FW ROM, YOSEMITE ID		
GC SCAN, DIS		
GRKL BUFS, 16244		
I/O OSC, STD SOURCE		
I2C VOLT, +3.3V		
IDE LED, ENA		
IRDA, DIS		
LED PWR, +5V		
PADDTON, ENET FAST		
PCI66, NORM		
ROM BOOT, AUTO		
ROM ENET, DUAL ADR		
ROM FLASH, PROD		
SCLKS, NORM		
SFT PWR, PS/2		
TST CON, ICT		
UATA 0646U2-402		
UATA CE, SW ENA		
UATA CHRDY, ASYNC		
UATA CLK, CMOS		
UATA DEV TYPE, NATIVE		
UATA DEV, STORAGE		
UATA LED, ENA		
UATA PCIMODE, NORM		
UATA REQ FIX, BYP		
USB CLK, MAIN CLK		
USB CONN, FOXCONN 2		
USB LED, ENA		
USB PWR, SWITCH		
The bom options that were copied to this file were:		
CTL BUF, IDT-ALVCH (ALT)		
ADR BUF, PHL-ALVCH (STD)		
USB IC, LUCENT		
USB IC, OPTI		
ADR BUF, IDT-ALVCH (ALT)		
CTL BUF, PHL-ALVCH (STD)		



SPEAKER AUDIO STAR GROUND
(CONNECTION POINTS)

PART NUMBER	QTY	DESCRIPTION	ASSOCIATED REFERENCE DESIGNATORS	BOM OPTION
609-0066	1	SPKR ASSY, YOSEMITE	J34	SPKR, ASSY YOSEMITE ENA
731-0062	1	SPKR, 8-OHM, 2W, 40x70MM	J34	SPKR, DRVR ENA

SPEAKER SUPPORT


Mono Amp & Speaker Connector


ECS CAD GENERATED
APPLE CONFIDENTIAL

NOTICE OF PROPRIETARY PROPERTY
THE INFORMATION CONTAINED HEREIN IS THE PROPRIETARY
PROPERTY OF APPLE COMPUTER, INC. THE POSSESSOR
AGREES TO THE FOLLOWING
(I) TO MAINTAIN THE DOCUMENT IN CONFIDENCE
(II) NOT TO REPRODUCE OR COPY IT
(III) NOT TO REVEAL OR PUBLISH IT IN WHOLE OR PART




SIZE	DRAWING NUMBER	REV.
D	051-0777	C
SCALE NONE	SHT 40 OF 43	





DVD INPUT CAP SUPPORT				
PART NUMBER	QTY	DESCRIPTION	ASSOCIATED REFERENCE DESIGNATORS	BOM OPTION
127S1008	2	CAP, TANT, 1UF, 10V, 10%	C430, C434	DVD CAP, TANT
132S1063	2	CAP, CER, 1UF, 10V, 10%	C430, C434	\$DVD CAP, CER




DVD Analog and Digital Inputs


ECS CAD GENERATED
APPLE CONFIDENTIAL


NOTICE OF PROPRIETARY PROPERTY
THE INFORMATION CONTAINED HEREIN IS THE PROPRIETARY
PROPERTY OF APPLE COMPUTER, INC. THE POSSESSOR
AGREES TO THE FOLLOWING
(I) TO MAINTAIN THE DOCUMENT IN CONFIDENCE
(II) NOT TO REPRODUCE OR COPY IT
(III) NOT TO REVEAL OR PUBLISH IT IN WHOLE OR PART

Apple Computer, Inc

SIZE	DRAWING NUMBER	REV.
D	051-0777	C
SCALE	SHT 37 OF 43	
NONE		







ECS CAD GENERATED
APPLE CONFIDENTIAL

NOTICE OF PROPRIETARY PROPERTY
THE INFORMATION CONTAINED HEREIN IS THE PROPRIETARY PROPERTY OF APPLE COMPUTER, INC. THE POSSESSOR AGREES TO THE FOLLOWING:
(i) TO MAINTAIN THE DOCUMENT IN CONFIDENCE
(ii) NOT TO REPRODUCE OR COPY IT
(iii) NOT TO REVEAL OR PUBLISH IT IN WHOLE OR PART

Apple Computer, Inc.

SIZE	DRAWING NUMBER	REV.
D	051-0777	C
SCALE	SHT 33 OF 43	
NONE		

USB Soft Power-On

