



Tech Info Library

Printing from Visicalc III

The driver file on the Visicalc III diskette is set up with two drivers: .PRINTER, which is the default printer driving the Silentype, and .QUME, the driver for the RS-232 port. Two ways to get output to the Qume are:

- A. Use the System Configuration Program to rename the existing .PRINTER to .SILENTYPE, then rename .QUME to .PRINTER.
- B. Send the information to the printer as if it were a file.

For the Silentype:

```
/P
P
```

For the Qume:

```
/P
F
.QUME
```

Then enter the lower right coordinate of the part of the worksheet you want printed.

Apple Tech Notes

Keywords: <None>

This information is from the Apple Technical Information Library.

19960215 11:05:19.00

Tech Info Library Article Number: 626