



Tech Info Library

Newton 2.0 OS: Trouble Beaming to 1.3 OS Device (12/95)

Article Created: 11 December 1995

TOPIC -----

When attempting to Beam My Card (an option in the Routing button of the Names application), the MessagePad being beamed to presents a -48006 error if the MessagePad is using Newton 1.3 OS.

DISCUSSION -----

This is something that Apple is currently investigating. Here is a workaround, so you can beam cards between Newton 2.0 and 1.3 OS devices.

Step 1

On the Newton 2.0 OS device, open the Extras drawer and tap on Owner Info.

Step 2

Check the owner.

Step 3

Tap on the routing button, and then tap on "Beam". DO NOT tap on "Beam My Card."

Step 4

On the Newton 1.3 OS device, open the Extras drawer, and tap on "In Box".

Step 5

Tap the Receive button, then tap on "Beam".

Support Information Services
Copyright 1995, Apple Computer, Inc.

Keywords: knmp

=====

This information is from the Apple Technical Information Library.

19960215 11:05:19.00

Tech Info Library Article Number: 19051