



# Tech Info Library

## GS/OS: How To Use It With A ProFile

This article last reviewed: 22 December 1988

This article shows you how to use GS/OS with a ProFile hard disk drive. Before beginning, make sure that:

- The ProFile Interface Card has the 341-0299 ROM. (See Tech Info Library article "GS/OS: Needs Latest ROM Revision To Work With ProFile" for further information.)
- The ProFile Interface Card has been modified for use with the Apple IIGS. (See Tech Info Library article "Apple II ProFile Interface Card Modification for the Apple IIGS" for further information.)

NOTE: The Partition and Zero option of the Advance Disk Utility does not work with the ProFile; it works with SCSI drives only.

### Procedure for Using GS/OS With a ProFile

-----

Follow these steps:

1. Select a slot for the ProFile Interface Card (this procedure uses slot 7).
2. Install the ProFile Interface Card and turn on the Apple IIGS.
3. Press Apple-Control-Esc to enter the Control Panel. In the Control Panel, under the SLOTS item:
  - a. Set SLOT 7 to "Your Card".
  - b. Set STARTUP SLOT to "5".
  - c. Press Return, Esc, Return to exit from the Control Panel.
4. Turn the computer off.
5. Insert the Apple IIGS System Disk in the first 3.5-inch drive and the System Tools disk in the second 3.5-inch drive (if available).
6. Turn the computer on.
7. After the system starts up, the SYSTEM.DISK, SYSTEM.TOOLS, and ProFile

appear on the desktop.

NOTE: If the ProFile was not formatted for ProDOS, GS/OS asks if the volume should be initialized.

To initialize:

- a. Select "Initialize".
- b. Name the volume.

This should take only a few seconds.

8. Open the System Tools disk and run the Installer program.

NOTE for single-drive systems: Eject the System Disk and insert the System Tools disk. The Installer program prompts you with Eject/Insert dialog boxes.

- a. A list of items to install appears.
- b. Select "Install System Files".
- c. Use the "Volume" button to bring the ProFile disk name to the top right of the screen.
- d. Select "Install".

The Installer program copies the System files from SYSTEM.DISK and SYSTEM.TOOLS disks to the ProFile. Old System files are replaced, but Desk Accessories, Fonts, and other files in "SYSTEM FOLDER" are not deleted.

9. To add other items, such as the SCSI card or 5.25-inch drive:

- a. Select the item.
- b. Click Install.

10. Install a printer driver:

- a. Select the item.
- b. Click Install.

11. Set the Control Panel to start up from slot 7.

12. Restart the system using the ProFile.

The ProFile is now set up for use with GS/OS.

NOTE: If you copy applications to the ProFile, copy only the program and data files. Do NOT copy the System Folder from the application disks.

Copyright 1989 Apple Computer, Inc.

Keywords: <None>

=====

This information is from the Apple Technical Information Library.

19960215 11:05:19.00

Tech Info Library Article Number: 3465