



# Tech Info Library

## Prometheus ProModem 1200: Using it with all Apples

### Modem type:

AT&T 103/212A series; 1200 or 0-300 bps.

### Instruction set used:

Fully HAYES compatible.

### Hardware configuration:

Twelve LED characters and eight LED indicators on front panel give call, modem, and data status. Internal back-up battery provides back-up power for clock/calender, modem configuration, and auto-dial number storage in memory. Modem runs off of 117VAC, 60 Hz.

### Software configuration:

Microprocessor controlled intelligent modem with clock / calender set, help menu, number storage, auto-dial, and auto-answer functions.

### Interface type:

RS-232 DB-25S (DCE) connector, full or half duplex operation.

### Modem interface packages, by computer:

#### Apple IIe (Super Serial card):

Access II or other terminal software; straight through DB-25 cable interface (serial card configured as DTE equipment) for hardware connection.

#### Apple IIc:

Access II or other terminal software; Apple IIc to Imagewriter cable with modem eliminator cable for hardware connection.

#### Apple III:

Access III or other terminal software; straight through DB-25 cable for hardware connection.

#### Macintosh:

MacTerm or other terminal software; Macintosh to Imagewriter cable with modem eliminator cable for hardware connection.

#### Macintosh XL:

MacTerm or other terminal software; straight through DB-25 cable for hardware connection.

Keywords: <None>

=====

This information is from the Apple Technical Information Library.

19960215 11:05:19.00

Tech Info Library Article Number: 1337