



# Tech Info Library

## CCS-7710: Cable for Nec 3510 and 5510 Spinwriter (1/97)

Article Created: 11 July 1985

Article Reviewed/Updated: 28 January 1997

TOPIC -----

Listed below are the cable pinouts for connecting the CCS-7710 interface card to the Nec 3510 or 5510 Spinwriter printers.

DISCUSSION -----

Nec Spinwirter 3510

-----

CCS-7710	NEC 3510 SPINWRITER
----------	---------------------

3 <----->	3
-----------	---

4 <----->	19
-----------	----

7 <----->	7
-----------	---

6,8,20: Jumpered

Nec Spinwriter 5510

-----

CCS-7710	NEC 5510 SPINWRITER
----------	---------------------

3 <----->	3
-----------	---

4 <----->	19
-----------	----

7 <----->	7
-----------	---

5,6,8,20: Jumpered

CCS 7710 dip switch settings for Nec 5510

-----

All down except #3

NEC 5510 dip switch settings

-----

All down except #4,7,8

NEC 510 front panel switch settings

-----

Speed=h, parity=m, dup=f, set to remote.

\* These cable are for use with the Apple IIe computer.

Article Change History:

28 Jan 1997 - Reviewed for technical accuracy, revised formatting.

Copyright 1985-97, Apple Computer, Inc.

Keywords: <None>

=====

This information is from the Apple Technical Information Library.

ArticleID: TECHINFO-0001468

19970129 10:07:13.00

Tech Info Library Article Number: 1468