



Tech Info Library

CCS-7710: Cable for Daisywriter (1/97)

Article Created: 11 July 1985

Article Reviewed/Updated: 28 January 1997

TOPIC -----

Listed below are the cable pinouts for connecting the CCS-7710 interface card to the Daisywriter printer.

DISCUSSION -----

CCS-7710	DAISYWRITER (50 pin connector)
----------	--------------------------------

3 <----->	3
7 <----->	6
4 <----->	49

CCS-7710 dip switch settings

All on except #1

Daisywriter dip switch settings

TOP BANK: all off except #1

CENTER BANK: all off except #8,

BOTTOM BANK: all off except #2

* This cable is for use with the Apple IIe.

Article Change History:

28 Jan 1997 - Reviewed for technical accuracy, revised formatting.

Copyright 1985-97, Apple Computer, Inc.

Keywords: <None>

=====

This information is from the Apple Technical Information Library.

ArticleID: TECHINFO-0001474

19970129 10:07:13.00

Tech Info Library Article Number: 1474