



Tech Info Library

H-Series ColorMonitor: No Color after Board Replacement (3/94)

Article Created: 24 March 1994

* RESTRICTED: Apple Internal and Support Providers Only *
Not For General Public Release

TOPIC -----

I have replaced an H-Series ColorMonitor main logic board several times before getting one that worked. The last replacement board doesn't have color. Is there a problem with the boards, or just an adjustment I need to make?

DISCUSSION -----

There is a control on the main board labeled R507. It is situated in the center of the board just under the bell of the CRT. This control is sometimes not set correctly at the factory. It controls the level of the color signal to the CRT. The technician should make very slight adjustments to this control until color appears on the screen. It is safe to run the control to its fullest range in either direction. However, if the control is set too high, color bars will appear across the display.

Support Information Services
Copyright 1994, Apple Computer, Inc.

Keywords: <None>

=====

This information is from the Apple Technical Information Library.

19960215 11:05:19.00

Tech Info Library Article Number: 14974