



Tech Info Library

ImageWriter II: Switch Settings for Use with a Apple IIe

This article last reviewed: 15 July 1990

TOPIC -----

What are the proper settings for using an Apple IIe with a Super Serial Card to an ImageWriter II?

DISCUSSION -----

The settings should be:

Super Serial Card

SW1	1	off
	2	off
	3	off
	4	on
	5	off
	6	on
	7	on

SW2	1	on
	2	off
	3	off
	4	off
	5	on
	6	off
	7	off

Jumper block pointed toward terminal.

ImageWriter II

SW1	1	off
	2	off
	3	off
	4	off
	5	off
	6	on
	7	off
	8	off

SW2	1	on
-----	---	----

2 on
3 off
4 off

Cable: 590-0335 or 590-0556
Copyright 1991, Apple Computer, Inc.

Keywords: <None>

=====

This information is from the Apple Technical Information Library.

19960215 11:05:19.00

Tech Info Library Article Number: 7737